

SCIENTIFIC AMERICAN

[Entered at the Post Office of New York, N. Y., as Second Class Matter. Copyright, 1897, by Munn & Co.]

A WEEKLY JOURNAL OF PRACTICAL INFORMATION, ART, SCIENCE, MECHANICS, CHEMISTRY, AND MANUFACTURES.

Vol. LXXVII.—No. 10.
ESTABLISHED 1845.

NEW YORK, SEPTEMBER 4, 1897.

[\$3.00 A YEAR.
WEEKLY.]




Fig. 1.—AN EIGHT WHEELED TRUCK.




Fig. 2.—THE BELPAIRE BOILER.




Fig. 3.—ONE OF THE EIGHT MOTORS.




Fig. 4.—THE HEILMANN ELECTRIC LOCOMOTIVE.—[See page 152.]

Scientific American.

ESTABLISHED 1845

MUNN & CO., - - - EDITORS AND PROPRIETORS.

PUBLISHED WEEKLY AT

No. 361 BROADWAY, - - NEW YORK.

TERMS FOR THE SCIENTIFIC AMERICAN.

(Established 1845.)

One copy, one year, for the U. S., Canada or Mexico.....\$3.00
 One copy, six months, for the U. S., Canada or Mexico..... 1.50
 One copy, one year, to any foreign country, postage prepaid, £0 16s. 5d. 4.00
 Remit by postal or express money order, or by bank draft or check.
 MUNN & CO., 361 Broadway, corner Franklin Street, New York.

The Scientific American Supplement

(Established 1876)

is a distinct paper from the SCIENTIFIC AMERICAN. THE SUPPLEMENT is issued weekly. Every number contains 16 octavo pages, uniform in size with SCIENTIFIC AMERICAN. Terms of subscription for SUPPLEMENT, \$5.00 a year, for the U. S., Canada or Mexico. \$6.00 a year, or £1 4s. 8d., to foreign countries belonging to the Postal Union. Single copies 10 cents. Sold by all newsdealers throughout the country. See prospectus, last page. Combined rate for SCIENTIFIC AMERICAN and SUPPLEMENT will be sent for one year, to one address in U. S., Canada or Mexico, on receipt of seven dollars. To foreign countries, eight dollars and fifty cents a year, or £1 14s. 11d., postage prepaid.

Building Edition of Scientific American.

(Established 1885.)

THE BUILDING EDITION OF THE SCIENTIFIC AMERICAN is a large and splendidly illustrated periodical, issued monthly, containing floor plans and perspective views pertaining to modern architecture. Each number is illustrated with beautiful plates, showing desirable dwellings, public buildings and architectural work in great variety. To architects, builders, and all who contemplate building this work is invaluable. Single copies 25 cents. By mail, to any part of the United States, Canada or Mexico, \$2.50 a year. To foreign countries, \$3.00 a year, or £2 12s. 4d. Combined rate for BUILDING EDITION with SCIENTIFIC AMERICAN, to one address, \$5.00 a year. To foreign countries, \$6.50 a year, or £2 16s. 9d. Combined rate for BUILDING EDITION, SCIENTIFIC AMERICAN, and SUPPLEMENT, \$9.00 a year. To foreign countries, \$11.00 a year, or £2 5s. 2d., postage prepaid.

Export Edition of the Scientific American

(Established 1875)

with which is incorporated "LA AMERICA CIENTIFICA E INDUSTRIAL," or Spanish edition of the SCIENTIFIC AMERICAN, published monthly, uniform in size and typography with the SCIENTIFIC AMERICAN. Every number contains about 100 pages, profusely illustrated. It is the finest scientific industrial export paper published. It circulates throughout Cuba, the West Indies, Mexico, Central and South America, Spain and Spanish possessions—wherever the Spanish language is spoken. THE SCIENTIFIC AMERICAN EXPORT EDITION has a large guaranteed circulation in all commercial places throughout the world. \$3.00 a year, or £0 12s. 4d., postage to any part of the world. Single copies, 25 cents.

MUNN & CO., Publishers, 361 Broadway, New York.

The safest way to remit is by postal order, express money order, draft or bank check. Make all remittances payable to order of MUNN & CO.

Readers are specially requested to notify the publishers in case of any failure, delay, or irregularity in receipt of papers.

NEW YORK, SATURDAY, SEPTEMBER 4, 1897.

Contents.

(Illustrated articles are marked with an asterisk.)

Archaeological news.....	150	Human structure, the.....	147
Archæology.....	147	Inventions recently patented.....	156
Art, landscape, the field of.....	154	Iron trade, the American.....	146
Boat, the, under the sea.....	150	Locomotive, Heilmann electric*.....	145
Body, care of the human.....	154	Logic and stage illusions*.....	155
Boiler locomotive, Belpaire*.....	145	Mathematics and physics.....	151
Boilers, flash (7200).....	156	Milk, Pasteurizing at home.....	147
Books, new.....	158	Motor of electric locomotive*.....	145
British Association meeting.....	146	Mount St. Elias ascended.....	154
Burner, Bunsen, improved.....	149	Mummy, the, of a Pharaoh.....	154
Calcium carbide, value of.....	147	Negligence, in law.....	151
Castings, shrinkage of.....	149	Notes and queries.....	156
Condenser, a steam engine*.....	148	Paris exposition, the, 1900.....	147
Corking device, Von der Linden*.....	148	Patents granted, weekly record.....	157
Corner piece for rooms.....	150	Pension figures, some.....	155
Electric cable in London.....	152	Plants, the sleep of.....	151
Electric locomotive, the Heilmann*.....	145, 152	Range finders, two new.....	148
Electric power transmission plan, Pennocks.....	149	Reamers, tempering (7201).....	156
Element, another looked for.....	147	Reindeer, the Alaskan.....	151
Excavations at Treves.....	150	Science notes.....	150
Exposition, 1898, Nebraska.....	154	SCIENTIFIC AMERICAN in Russia.....	152
Fire, how it causes death.....	147	Scientists, meeting of.....	146
Fuel supply, the world's.....	147	Sculptor's profits, the.....	155
Geography.....	147	Spiritualistic post test, a*.....	155
Grand Central Station, the.....	149	Surgical operations, time for.....	148
House building by ritual*.....	153	Torpedo, firing a*.....	155
		Truck of electric locomotive*.....	145
		Valve, reversing, Roy's*.....	148
		Vinegar, aromatic (7203).....	156

TABLE OF CONTENTS OF

Scientific American Supplement

No. 1131.

For the Week Ending September 4, 1897.

Price 10 cents. For sale by all newsdealers.

I. AGRICULTURE.—Preservation of Fresh Grapes and Seed Potatoes in Italy.....	18083	PAGE
II. ARCHEOLOGY.—Address by Sir JOHN EVANS.—An Important Archaeological Resume, with a Portrait of Sir John Evans.—1 illustration.....	18081	
III. ARCHITECTURE.—The New Russian Church at Karlsbad, Bohemia.—1 illustration.....	18079	
IV. BIOGRAPHY.—Edward Drinker Cope, Naturalist.—The third installment of the presidential address of Prof. GILL before the A. A. A. S.....	18080	
V. BOTANY AND HORTICULTURE.—Alpinia Nutans.—1 illustration.....	18083	
VI. ELECTRICITY.—Sectorless Wimshurst Machines.—By S. M. KEENAN.—A valuable article for amateurs who are interested in static electricity.—4 illustrations.....	18072, 18086	
Electrification by Uranium.—1 illustration.....		
The Trial of the Marconi Telegraph at Spezia.—A most interesting account of the experiments that Signor Marconi conducted at Spezia, with a view taken from a photograph showing Marconi's work.—2 illustrations.....	18071	
VII. FUELS.—Moisture in Coal.....	18074	
VIII. MECHANICAL ENGINEERING.—Cold Saw for Crank Webs.—1 illustration.....	18075	
IX. METALLURGY.—Aluminum in Knitting Machinery.—By GEORGE D. RICE.—An important article on making and finishing small aluminum castings.—1 illustration.....	18075	
A Rapid Method for the Determination of Silicon in Silico-Spiegel and Ferro-Silicon.....	18075	
X. MISCELLANEOUS.....		
Electrical Notes.....	18085	
Miscellaneous Notes.....	18085	
Selected Formulae.....	18085	
XI. OPTICS.—Ultimate Optical Efficiency.—1 illustration.....	18086	
XII. PERPETUAL MOTION.—Perpetual Motion, II.—The second installment of this interesting and important series.—6 illustrations.....	18076	
XIII. PHOTOGRAPHY.—Underground Photography.—This article is illustrated with flashlight photographs in mines and is accompanied by illustrations of the apparatus used.—4 illustrations.....	18074	
XIV. SCIENCE.—The Science of Humanity.—By W. J. MCGEE.—Of the science of animal man.—The second installment of this address, treating of the science of animal man, the activities of man, etc.....	18083	
XV. SUBMARINE EXPLORATIONS.—Description of a Closing Tow Net, for Submarine Use at all Depths.—By C. H. TOWNSEND.—A full description of an ingenious device for submarine exploration.—8 illustrations.....	18073	
XVI. TECHNOLOGY.—Acidproof Cement.....	18084	
XVII. TRAVEL AND EXPLORATION.—The Stockholm Exhibition.—2 illustrations.....	18078	
The Subsistence Question in the Klondike Region.—A very important article by an authority, giving information of interest to all who think of going to the new gold regions.—The statistics are very complete.....	18079	

THE AMERICAN IRON TRADE FOR 1896.

If a copy of the statistics of the American Iron Trade for 1896 were put into the hands of a student fresh from a course of lectures on political economy, his belief in one of the cardinal truths of this science would be liable to receive a rude shock in the first few pages of the pamphlet. If the "cost of production determines the selling price," how comes it, he will ask, that the first pages of the "statistics" are taken up very largely with an account of various influences which caused the violent fluctuations in price of the past year? The "wire nail pool" came to an end about December 1, 1896, and "prices dropped rapidly." Its fate is shared by the "billet pool," and a similar fall in prices is noted. In May the "beam pool went to pieces" and prices experienced a simultaneous fall. An examination by the author of the statistics into the causes of low prices and depression leads to the conclusion that, though some of them may be "occult and intangible," there are two that are plainly visible—the distrust of the country's future due to the silver movement, and the pressure upon prices and profits of a capacity of production which is greatly in excess of our powers of consumption. A similar cause to the last is the reckless construction of unnecessary railroads which have since become bankrupt; and the wrecking of other railroads, which were needed, by hostile State and national legislation is also noted.

It is satisfactory to note the great increase which has taken place during the last few years in both our exports and manufactures of iron and steel. This has been particularly marked in the calendar years 1895 and 1896, our exports for these years being respectively \$35,071,563 and \$48,670,218. In each of the last four years our exports have exceeded our imports, the aggregate exports amounting to \$143,844,873 and the aggregate imports being \$95,778,838. The decline in imports is due to decreased demand for foreign tin plates and to the low price of our iron and steel. Our increased exports are due to the same low prices, though this increase has brought no appreciable relief to our glutted markets.

Since the close of the civil war there have been four periods of particularly low prices for iron and steel, the first occurring after the panic of 1873. The rate given in the following table is per long ton, except for bar iron, which is quoted by the 100 pounds.

Articles.	1873-9.	1884-5.	1891-5.	1896-7.
No. 1 foundry pig iron, at Philadelphia.....	\$16.50	\$17.50	\$12.00	\$11 75
Gray forge pig iron, lake ore, at Pittsburgh.....	16.00	14.00	8.90	8.50
Bessemer pig iron, at Pittsburgh.....	19.50	17.00	9 95	9.25
Old iron T rails, at Philadelphia.....	18.00	16.50	11.00	11.50
Best bar iron, at Pittsburgh.....	1.60	1.50	1.10	1.05
Steel rails, at mills, in Pennsylvania.....	40.00	26 00	22.00	17 00

There is a decrease in the production of all kinds of material except open hearth steel. There was a decrease of 5 per cent in the amount of iron ore mined; the output of pig iron decreased 8.7 per cent; Bessemer steel ingots, 20.1 per cent; other steel than open hearth decreased 13.6 per cent; structural shapes, 4.3 per cent; Bessemer rails, 14 per cent; wire rods, 21.1 per cent; wire nails, 19.1 per cent; cut nails, 24.1 per cent; open hearth steel (the one exception) showing an increase of 14.2 per cent. The following table gives the totals of production for the years 1895 and 1896:

	Total production.	
	1895.	1896.
Pig iron.....	9,446,308	8,623,127
Bessemer steel ingots.....	4,909,128	3,919,906
Structural shapes.....	517,920	495,571
Open hearth steel.....	1,137,182	1,298,700
Crucible steel.....	67,666	60,689
Bessemer rails.....	1,299,628	1,116,958
Wire rods.....	791,130	623,986
Wire nails.....	5,841,408 kegs	4,719,860 kegs
Cut nails.....	2,129,894 "	1,615,870 "

Although there has been a decrease of nearly a million tons in the total production of pig iron, it is noteworthy that the growth of the industry in the Southern States continues, Alabama, Virginia and Tennessee coming fourth, fifth and sixth in the list. Pennsylvania, of course, stands first, its output being 4,024,166 tons or 46 per cent of the total production of pig iron in 1896; Ohio produced 14 per cent; Illinois and Alabama each produced over 10 per cent of the total, and Virginia over 4 per cent. All the other States fell below 3 per cent. The largest falling off is in Pennsylvania, where the decrease was over 675,000 tons.

There is a small increase in the production of Bessemer steel compared with the averages of recent years, which has been somewhat more than 3,500,000 tons. The falling off in the production of Bessemer steel rails will not surprise any one who is familiar with recent railroad history and present conditions in this country. The extraordinary activity in railroad construction between the years 1885 and 1892, when the total construction for one year alone reached a total of over 12,000 miles, will explain the enormous demand for steel rails. At the close of that period some of the ablest railroad men in the country gave warning that the country was being over-supplied and stated that most

of the country contained more railroads than would meet its needs for the next quarter of a century. The disaster which speedily overtook a large proportion of the roads, and the present depressed condition of those that did not go into the hands of receivers, has verified their forecast of the situation, and explains the great falling off in the total production of Bessemer rails. The total mileage upon which rails were laid in 1895 was 1,922 miles and in 1896 it was even less, being only 1,850. These figures are the lowest since the year 1875. Pennsylvania leads the States in the production of rolled iron and steel, having made 56.8 per cent of the total production of rolled iron and steel in 1896, against 56.4 per cent in 1895; Ohio made 13.9 per cent in 1896, against 14.4 per cent in 1895; Illinois made 10.7 per cent in 1896, against 10.1 per cent in 1895; and Indiana made 3.5 per cent of the total product in 1896. No other State produced 3 per cent in that year. Texas and Iowa were the only States having rolling mills located within their borders which did not roll either iron or steel in 1896.

One of the most interesting tables in the statistics is that of the world's great pig iron producers. In 1869 the United States produced 1,711,287 tons, Great Britain 5,445,757 tons, and Germany and Luxemburg combined 1,409,429 tons. A dozen years later, in 1881, the United States produced 4,144,254 tons, Great Britain 8,144,449 tons, and Germany and Luxemburg 2,914,009 tons. In the following ten years the United States not only doubled its own output but surpassed the total for Great Britain, the respective totals being 9,202,703 and 7,904,214 tons, Germany and Luxemburg producing 4,658,450 tons. We lost the lead to Great Britain in 1894 but regained it the following year, when we reached our maximum figure of 9,446,308 tons. The figures for 1896 are: United States, 8,623,127 tons; Great Britain, 8,563,209 tons; and Germany and Luxemburg, 6,374,816 tons. Of late years the most striking fact has been the rapid advance of the industry in other countries than the United States and Great Britain. At present, out of a total world's production of about 16,500,000 tons of crude steel, the latter countries together produce more than 9,500,000 tons, while all other countries combined produce 7,000,000 tons. When we bear in mind that half a dozen years ago all other countries produced only 4,400,000 tons, it is evident that if the present rates of increase continue, the combined output of the United States and Great Britain will be less than that of the rest of the world combined.

THE BRITISH ASSOCIATION MEETING.

To all who are interested in the promotion of useful knowledge for the general benefit of the race, the annual meetings of the British Association for the Advancement of Science have come to be looked forward to as seasons of special advantage, rich alike in their unfolding to the popular eye of the progress made in many branches of science for the preceding year and the promises held out and guide marks placed for future advancement.

In our last week's issue we gave a summary of the principal papers discussed at the meeting of the American Association, working on similar lines, and held a week earlier. The British Association meeting was held at Toronto, Canada, its sessions continuing from August 18 to August 25. The fact that the meeting this year was held on this side of the Atlantic, and that it came so soon after the magnificent celebration of the Queen's Jubilee, contributed not a little, no doubt, to the splendid enthusiasm with which the visiting scientists were received by our Canadian neighbors, and which was heartily participated in as well by a large delegation of American representatives of scientific advancement. The occasion also brought vividly to mind the former meeting of the British Association at Montreal, in 1884, the first that had ever been held outside of the United Kingdom, and the ensuing series of visits then made by representative foreign scientists to various great industrial establishments and notable engineering works in the United States. It was then that, for the first time, the gigantic strides which this country was making in many lines came to be fully appreciated, and, in the iron and steel manufacture, especially, it was felt that we were not only dangerous competitors in a field where England had heretofore claimed undoubted primacy, but that we were working in a direction and with a skill likely to give us the lead. The facts then so plainly set forth have acted as a spur to foreign manufacturers ever since, and consumers everywhere have reaped the benefit in better goods at lower prices.

At the meeting this year among the eminent foreigners present were Lord Kelvin, Lord Rayleigh, Prof. Roberts-Austen, and Messrs. Preece and Lodge, the famous electricians; Lord Lister, the father of antiseptic surgery, and last year's president; Prof. William Ramsay, who was associated with Lord Rayleigh in the discovery of argon, and who alone is entitled to the glory of first finding helium in terrestrial minerals; Sir John Evans, the new president; Prof. John Milne, recently of the University of Tokio, where he investigated the phenomena of earthquakes extensively; Prof. William Cawthorne

Unwin, one of the engineering experts who counseled the Cataract Construction Company when Niagara was harnessed; Sir Bosdin Leech, chief engineer of the Manchester Ship Canal; Prof. James Bryce, author of "The American Commonwealth;" and sixty or seventy others, who enjoy a high reputation in England, Scotland or Ireland, by reason of their professional activity in some department of science. A great many public and social or semisocial functions, with various excursions to different points of interest, including a visit to the Niagara Falls power plant, were pleasant features of the occasion, into which all seemed to enter most enjoyably.

In his opening address the president, Sir John Evans, said that he would undertake no general review of recent scientific progress, but would discuss a question belonging to his own special field of study.

ARCHÆOLOGY.

The relations which chemistry, mineralogy and history bore to this science, he said, were important, but the aid of geology and paleontology was imperative, if one inquired into the antiquity of man. When in 1859 human remains were found in the valley of the Somme, in France, in gravels that also yielded bones of the mammoth and the woolly rhinoceros, the coexistence of man with these animals in the quaternary period was established for a time. After the first excitement had subsided, there was a tendency among scientists to cut down the lapse of ages necessary to account for the changes in the earth's surface which had occurred since those gravels were deposited. He, however, sympathized with the view taken by Sir Charles Lyell that such penuriosity was a mistake. Many at the present day had got over this feeling, and of late years the general tendency of those engaged on the questions had been in the direction of seeking for evidence by which the existence of man on earth could be carried back to a period earlier than the quaternary gravels. The speaker cited some of the attempts in this direction. He was himself not satisfied with the supposed discovery of flint implements in pre-glacial deposits in the eastern counties of England, because they resembled too closely those of post-glacial times there, nor could he yet accept the evidence of the Norfolk Pliocene forest bed, where flints had been found within a few months that looked as if they had been worked by human hands. This alleged discovery and similar ones in France, Italy and Portugal were accepted by some geologists, but they were too few and too isolated to satisfy Sir John. Nevertheless, he did not despair of obtaining proof of man having lived in the tertiary period. Sir John did not indulge in specific figures, but effectively emphasized the remoteness of time to which belonged the earliest blunt stone implements of the paleolithic era in western Europe. He believed, however, that man existed before this in southern and eastern Asia. This, in fact, he considered the birthplace of the race, and he favored special investigations in that part of the globe.

This address will be published entire, as well as the other most valuable papers presented at the meeting, in current issues of the SCIENTIFIC AMERICAN SUPPLEMENT.

GEOGRAPHY.

Before the geographical section, Dr. J. Scott Keltie, for many years secretary of the Royal Geographical Society, said he considered the present problem of this science in Europe, the region most in need of exploration being Albania. In Asia there was work to be done in the Malay Peninsula and Southern and Central Arabia. But the chief stress was laid upon the district lying between the Himalayas and the forbidden city of Lhasa, in Thibet. Parts of China, too, were still a blank on the maps, and there was something to learn about the source of the Irrawaddy River. In Africa it was desirable to explore the Central and Western Sahara, the region south of Abyssinia and northwest of Lake Rudolf and the highlands of British East Africa. On the latter Dr. Keltie remarked that it might be necessary to find homes for future generations when the United States and Canada became over-populated. The discovery by the young geographer and biologist, Moore, of salt water fauna near Lake Tanganyika, showing that that country had once been beneath the ocean, was an important revelation and indicated what fine surprises yet awaited the intelligent investigator. In the Arctic region the archipelago of North America was one now most needing attention. The speaker enlarged also on the desirability of studying Antarctic territory.

MATHEMATICS AND PHYSICS.

In this section Prof. A. R. Forsyth, of Cambridge University, made a forcible plea for the study of mathematics, not only in its relation to other branches of knowledge, but for its own sake. Lord Kelvin dwelt on the immense practical importance of mathematics, and said such work as harnessing Niagara was impossible without a thorough grasp of the higher mathematics. He dwelt, too, on the rapid spread of the study of this science by engineers in the last twenty years. An hour later an eminent city engineer of Liverpool, George Frederick Deacon, uttered an opinion seemingly contradictory to Lord Kelvin's. Mr. Deacon once

worked in the laboratory of Sir William Thomson (now Lord Kelvin), and accompanied the latter on the expedition which laid the first successful Atlantic cable, in 1865. As president of the mechanical science section he discussed the education which young engineers ought to have. He commended the technical schools of the United States and Canada as superior to many in England in extent of the workshop practice provided for students. This he considered more valuable than some of the mathematical training given them. College bred men were not always the most successful engineers. Well directed observation and long experience were secrets of success.

THE WORLD'S FUEL SUPPLY.

At another session of this section, Lord Kelvin discussed the world's fuel supply and air supply in a highly original manner. By fuel he meant not only heat, coal and oil, but existing forests and mould; in fact, all ancient and modern vegetation. Referring to the familiar phenomenon of plant life, that it absorbs carbonic acid and throws off oxygen, he argued there was possibly, even probably, a distinct relation between the amount of oxygen gas in the earth's atmosphere and the amount of vegetation past and present. Three tons of oxygen are required to burn one ton of standard fuel. Consequently, he would assume that for every three tons of oxygen in the air one ton of fuel had come into existence. The outcome of this rough computation was 340,000,000 tons of fuel.

PROF. RAMSAY LOOKING FOR ANOTHER ELEMENT.

Prof. William Ramsay, of London, who divides with Lord Rayleigh the honor of discovering the new element in the atmosphere which they named argon, presided over the chemical section. His address was devoted to showing why he expected still another element would in time be found resembling both helium and argon in some respects. Chemists were familiar with several groups of three elements each, in which the difference in atomic weight between the first and the third members was 36. The atomic weight of helium was first placed at 4, and that of argon at 40. Eventually both of these figures would be reduced somewhat, but the interval would probably remain about the same. He was thus led to believe that another member would be found for this group to fill a vacancy between helium and argon. Such discoveries, based on Mendeleef's "Periodic Law," have been predicted and made before this. Prof. Ramsay and his assistant have already examined an extraordinary number of substances in the hope of finding the unknown gas, but so far without success. The speaker expressed his own confidence in the soundness of Mendeleef's law, in spite of some discrepancies between the actual atomic weights of many elements and the weights which the theory demands.

THE HUMAN STRUCTURE.

In the anthropological section, its president, Sir William Turner, of Edinburgh, spoke of "Some Distinctive Characters of Human Structure." Some of the peculiar features of man's frame, he said, are the curvature of his spine, the crooked way in which the thigh bone fits into the hip, the greater freedom and grace of the movements of the legs than are possible with apes and lower animals, the more highly developed hand and certain characteristics of the foot. All of these, interesting and significant as they are, are overshadowed by the superiority of the brain in relative weight and in complicated structure. Boys' brains at birth weigh more than girls'. The brains of men of intellectual eminence weigh fifty-five or sixty ounces on the average, while imbeciles may have only thirty ounces. The mean internal capacity of the craniums of adult Europeans is about one thousand five hundred cubic centimeters, and in Australian aborigines one thousand two hundred and eighty. That of adult male gorillas is about four hundred and ninety.

THE PARIS EXPOSITION OF 1900.

The French stand easily first among the peoples of the world in the matter of getting up fetes and shows and in arranging pageants which shall have the highest spectacular effects. The world of fashion has always looked to Paris for its leaders, and those in pursuit of pleasure for its own sake have made their Mecca on the banks of the Seine. How much of the idea of the Paris Exposition of 1900 is to be attributed to the desire to make of it something far larger and more splendid than ever before achieved, with the view of making Paris itself more attractive, and how much is due to French ambition for a comparison of their educational, industrial and material progress with the best the world can show, it is not at all important to define. The French government and people are working to make the exposition one which will far surpass all its predecessors, as well in the extent and variety of the exhibits as in the pomp and magnificence of the splendid accompanying fetes and entertainments, and it is safe to say that never before were plans for such a project more thoroughly elaborated or more completely worked out, down to the finest detail.

The importance of a good representation of the United States at the exposition is generally conceded,

primarily, from the fact that our growth in many lines of manufacture has now reached such proportions that further material increase cannot well be looked for, unless we can sell largely in foreign as well as the home markets.

Our ability to successfully compete with foreign manufacturers in their own markets, in many lines of manufactured goods, cannot be doubted, and some efforts in this direction have already met with marked success, but the exposition will afford an opportunity to put such representation on a better basis, and to effectively bring American goods more thoroughly before foreign buyers than ever before. To the end, therefore, that our participation in the exposition may be fully representative, and that American manufacturers may have sufficient space allotted them, Major Handy, the United States commissioner, intends to apply for 500,000 feet to be devoted to exhibits from the United States.

Commissioner Handy sailed for Europe last week, intending to return and report to Congress at its next session, giving all available information to intending exhibitors, and asking for a liberal appropriation from the government, that the United States may be creditably represented.

MOUNT ST. ELIAS ASCENDED.

Prince Luigi of Savoy and his party of Italian mountain climbers are now on their way back to Italy after accomplishing the feat of scaling Mt. St. Elias. The party included Prince Luigi, Lieut. Cagni, Dr. Phillippi and Vittorio Sella, the well known photographer of mountain views. The expedition sailed from Seattle in June and reached Yakutat Bay on July 22. A landing was made with some difficulty and the overland trip was begun. They took with them over 6,000 pounds of provisions. After six days travel inland Malaspina glacier was reached. The glacier is twenty miles wide, and it took four days to cross it. They crossed various other glaciers and passes and finally reached Mt. St. Elias. At the foot of Mt. Newton glacier the American party of Mr. Bryant was met; they had abandoned the project and were returning. Here the Italian members of Prince Luigi's party were left. The prince was, it seems, jealous that any save his countrymen should have the honor of climbing with him the summit of the lofty mountain, which was ungracious, to say the least.

The ascent of Mt. St. Elias began on Friday, July 30, and after seven hours hard climbing they arrived at the top of the divide; here a tent was pitched and a few hours of much needed rest were taken. Then the ascent began again, and four hours from the divide saw them standing on the top of the mountain. About two hours were spent on the peak, and during this time much was done in the way of scientific observations and Signor Sella secured some very fine negatives from the summit. The descent occupied about two hours, the mountaineers sliding most of the way down, and the camp was reached at nightfall. The dreary backward journey over the glaciers was accomplished without accident. The actual height is, according to Prof. Davidson, 18,060 feet. A number of previous attempts have been made to ascend Mt. St. Elias, which was discovered by Behring on St. Elias day, 1741.

WILL ASCERTAIN THE VALUE OF CALCIUM CARBIDE.


The American Druggist and Pharmaceutical Record, under the head of "Tariff Problems Considered," says the Treasury Department will send out a special agent to make an investigation of the value and market price of calcium carbide. This article is used in the manufacture of acetylene gas, a product which is now being extensively exploited by a large syndicate, which controls the patents under which it is manufactured. The tariff law levies an ad valorem duty on this product, and, as it has been brought in at several ports, collectors have varied more than 200 per cent in their valuations; but in all cases have materially exceeded the invoice valuation. The company controlling the patents have an important interest in keeping the apparent cost of the article as low as possible, as they are disposing of royalties in nearly all the States, and the economy of production necessarily depends upon the cost of the raw material. In view of the limited supply and circumscribed market, the department sees no way of ascertaining the value of the article without a special investigation.

The American and British Associations' Addresses and Papers.

Attention is called to the fact that in the SUPPLEMENT of last week and in the current issue there are a number of addresses and papers which were read at the meeting of the American Association for the Advancement of Science and at the British Association. Thus in the current number will be found a continuation of Prof. Gill's "Edward Drinker Cope, Naturalist," the presidential address by Sir John Evans before the British Association and the conclusion of Prof. W J McGee's "The Science of Humanity." In next week's SUPPLEMENT these papers will be continued and others will be begun.

A CONDENSER FOR STEAM ENGINES.

The illustration represents a condenser arranged to prevent the water from accumulating in the condenser casing, irrespective of the working of the pump, and without causing back pressure on the engine. It has been patented by William T. Snell, Laurium, Mich. It has a closed casing from whose bottom extends a suc-



SNELL'S CONDENSER FOR STEAM ENGINES.

tion pipe connected with a pump, and in the casing is a bell-shaped float on whose upper end is a vertical stem connected with a spraying nozzle sliding in a pipe leading to the water supply, the rise and fall of the float thus shutting off or regulating the admission of the cooling water. On the upper end of the condenser is also a valve casing connected with the exhaust pipe of the engine, the casing having two valves attached to a common valve stem, whose vertical movement causes the steam to be passed into the condenser or to the outer air. A coiled spring near the upper end of the valve stem holds it normally in uppermost position, the steam then passing into the condenser; and on the lower end of the stem, within the condenser casing, is a collar adapted to be engaged by an arm which is vertically adjustable on the stem extending upward from the float. In case the water accumulates in the casing, from not being drawn off fast enough by the pump, the rising of the float shuts off the supply of cooling water, which is again admitted through the spraying nozzle, when the pump reduces the amount of water and the float moves downward. Should the water supply fail, or water be drawn from the casing faster than supplied, the sinking of the float would cause the arm extended from the stem of the float to engage the collar on the lower end of the valve stem in the casing connected with the exhaust steam pipe, thereby shutting off steam from the condenser and passing it out to the atmosphere. In the under side of the float, as shown in the broken-away portion in the engraving, is a small chamber into which extends the upper end of the suction pipe, permitting air bubbles to be readily drawn out, a spider on the bottom of the float forming a guide for the float on the fixed suction pipe.

TWO NEW RANGE FINDERS.

We illustrate herewith two range finders, invented by George M. Searle and George N. Saegmuller, of



SEARLE AND SAEGMULLER'S RANGE FINDER.—Fig. 1.

Washington, D. C., for which United States letters patent Nos. 588,093 and 588,094 were granted them August 10, 1897. The purpose of these devices is to determine the distance of remote objects, such as an enemy's vessel at sea, in a rapid and convenient manner, by means

of a scale on the instrument, and without the delay of calculation.

Fig. 1 is designed for use on the deck of a ship, or other horizontal surface, and its base line is horizontal; its principle of operation being that of a constant angle by means of an adjustable base line. It comprises a graduated base line bar having a fixed right angular reflecting prism at one end, and also a movable one, with a pointer, traveling on the graduated scale of the base line bar, said two reflecting prisms being in different planes to throw their images on different portions of the object glass of a telescope, and a telescope constructed to bring these two images into coincidence whenever the movable reflecting prism reaches the point on the scale indicating the distance of the object viewed.

Fig. 2 is designed to meet the conditions of range finding or distance measuring from an observation point aloft, on the mast head of a ship, for instance. The base line in this case is vertical, and is of a fixed and definite length. This range finder comprises a telescope, two reflecting prisms separated, in fixed relation, a distance apart representing a base line, and arranged in different planes, so that each sends its own rays upon a different portion of the object glass of the telescope; an axially adjustable refracting plate for receiving the rays from one of the reflecting prisms and bringing them into coincidence with the other rays of the other prism; a pointer fixed upon the adjustable refracting plate; and a cotangent scale of equal parts for marking equal spaces for variable distances. This latter device (Fig. 2) is being put upon the United States battleship Iowa, and great results are expected from it. From a preliminary test the following comparison of distances by triangulation and the range finder were obtained.

By Triangulation.	By Range Finder.
2154 yards	2140 yards
1814 "	1800 "
1212 "	1220 "
1184 "	1190 "
4300 "	4270 "

The instruments are being manufactured by George N. Saegmuller (Fauth & Company) Mathematical Instrument Works, No. 108 Second Street, S. W., Washington, D. C.




Fig. 2.
RANGE FINDER.

demand of the patient, etc., are a few of the points which seem to recommend an early hour; on the other hand, it is not to be denied that it may be a source of greater task upon the surgeon's powers, especially if he be concerned and anxious, as conscientious men always must be in regard to capital operations, and if this anxiety interferes with the operator's sleep. Even with this disadvantage, however, the operator is capable of doing really better work before he has become tired and annoyed by the various demands upon him during the early hours of the day. Consequently, those who have operated extensively in the early morning hours never volunteer any afternoon operations.

A REVERSING VALVE FOR ENGINES.

A reversing valve chest is, according to the improvement represented in the accompanying illustration, interposed between the ordinary cylinder and steam chest, and this valve chest contains a reversing valve and connecting ports, the device being readily applicable to any ordinary engine, although for new engines the reversing valve chest may be made integral with the cylinder or the steam chest. The improvement has been patented by David W. Roy, of Tucson, Arizona Territory, Fig. 1 representing it in side elevation and Fig. 2 in transverse section. The port at one end of the cylinder connects with two ports in the reversing valve chest, containing a reversing valve in the form of a plug valve, and the port at the other end of the cylinder connects with two other ports in the chest, and leading to the bore in which the valve is mounted to turn, the several ports of the valve being arranged opposite each other, but in pairs which lie in a different

vertical plane, and each pair connecting by different passages with ports leading to the steam chest, where the slide valve is operated from the main driving shaft of the engine in the usual manner. Between the ports leading to the steam chest is an exhaust port, and on the outer end of the plug valve is a handle by which the valve may be turned to the right or left for revers-




ROY'S REVERSING VALVE FOR ENGINES.

ing the engine, or moved to a vertical position for cutting off steam.

H. WILDE has exceeded his own estimated limit of 400 lb. per square inch for magnetic traction by means of annealed charcoal iron wire 0.57 in. in diameter. The electromagnet was excited by a current of 40 amperes. With a piece of wire 1.2 in. long the unprecedented tractive force of 422 lb. per square inch was obtained. That the magnetization limit was virtually arrived at was shown from the fact that, when the current transmitted round the electromagnet was reduced from 40 to 26 amperes, the amount of the tractive force remained constant. The determinations were made with a single pole electromagnet, says the Electrician.

INSERTING CORKS IN BOTTLES.

For driving corks into place in bottles, as may be necessary in small bottling establishments or where families preserve domestic products, the device shown in the accompanying illustration has been invented and patented by Charles von der Linden, of Rhinebeck, N. Y. Fig. 1 shows the device closed, applied to a bottle, and Fig. 2 shows it open. It has two tapering sections, pivoted to swing to open and closed position, the sections being held closed by a clamping arm, and the lower end of each section has a semicircular flange, the flanges forming a dish-shaped cavity adapted to receive the mouth of the bottle. A circular head closes the upper ends of the sections, and in an upwardly extending boss is held a sliding rod or plunger, to the upper end of which a hand knob is removably attached by a cotter pin. A washer of greater or less thickness is placed on the plunger below the hand knob, thus regulating the amount of vertical movement of the plunger. In use, the cork is placed in the open lower end of the device, when the sections are closed to hold the cork firmly, and the flanges are made to embrace the mouth



VON DER LINDEN'S CORKING DEVICE.

of the bottle, after which the hand knob is struck to drive down the plunger rod and force the cork into the neck of the bottle. To drive the cork completely down, flush with the mouth of the bottle, the washer is removed from the plunger rod.

The Grand Central Station.

This great headquarters and metropolitan station of the New York Central and Hudson River system is now being enlarged and changed as to its exterior in a most radical way, although the interior arrangement of the ground floor is not to be changed at present. The original building, not counting the more recently added train-receiving house, was 240 feet on Forty-second Street by 692 feet on Vanderbilt Avenue, built of brick, stone and iron, and costing nearly \$2,250,000. On the streets named it was three stories high and was surmounted by several Louvre domes, and three more stories are now to be added, giving a uniform height of six stories, the towers also to be carried up proportionately, except the clock tower, which is to be obliterated. The entire building will be faced with stucco work, giving it the appearance of Indiana limestone, and the improvement will cost in the neighborhood of \$700,000. The added room thus provided has long been needed for the use of the executive officers and the 500 to 600 clerks employed. It may be added that at the same time that this very considerable work is being carried on, employing a large force of men, the neighboring streets are also being occupied by the workmen and materials necessary in constructing the new underground trolley, by which many of our leading street railways are to be operated by electricity.

THE UMBRELLA BOAT.

The queer sailing vessel shown in our engraving is called the "umbrella boat," and is also known as the boat with the cyclone sail. This boat has been very conspicuous at Cowes and in the Solent. Our engraving was made from a photograph by West & Sons, Southsea, Eng. The chief feature of the cyclone sail is, it is said, that "the wind pressure does not tend to incline the boat. When the wind is making a large angle with the sail the center of pressure is almost at the center of the surface, but when the wind strikes the sail at an acute angle, as in all sails or kites, the center of pressure moves toward the weather edge; but, by suitably adjusting the sail, the desirable result of obliterating all heeling movement has been achieved.

"In practice this has been obtained by putting more sail to leeward than to windward of the mast and also by placing the sail not quite at right angles to the mast, but more raised on the lee side. The sail is made oval, with the major axis horizontal, so as to be able to carry more sail with a definite height of mast.

"The training in a horizontal direction is accomplished by means of a turntable, and the elevating and lowering by two tackles. There is a balance weight which helps in elevating the mast and which is just sufficient to balance the dead weight of sail in a calm not inclining the boat. The sail can be set and furled in a minute; it does not close like an umbrella, but each side shuts up like a fan. The object of the sail is to be able to sail without inclining the boat, so that the limit of driving force is not governed by the stability of the boat in any way, and also that the boat sailing on an even keel has less resistance than when sailing with a list."

In addition to the inventor's claim for his boat, the following particulars may be of interest: The sail in the illustration measures 30 feet horizontally and 16 feet up and down, while the total length of the boat is only 17 feet on the water line. With an ordinary rig 200 square feet of canvas was found too much for this boat, but with the umbrella sail she carries 360 feet of canvas and sails much faster. A light boat especially adapted for the sail is now being built by Messrs. Thornycroft, of Chiswick, England, the well-known manufacturers of torpedo boats.

Shrinkage of Castings of Metals.


Pure aluminum (13-64 inch).....	0.2031 inch to the foot.
Nickel aluminum casting alloy (3-16 inch)...	0.1875 " "
Special casting alloy of the Pittsburg Reduction Company (11-64 inch).....	0.1718 " "
Thin brass castings.....	0.167 " "
Thick " ".....	0.150 " "
Zinc.....	0.3125 " "
Lead.....	0.3125 " "
Copper.....	0.1875 " "

—Aluminum World.

AN IMPROVED FORM OF BUNSEN BURNER.


A great drawback with the ordinary form of Bunsen burner is the liability of the central jet to become choked up by anything falling down the tube, says Hugh Marshall, D.Sc., F.R.S.E., in the Journal of the Society of Chemical Industry. A single drop of water is often sufficient to extinguish the flame, and a fused borax bead is still more objectionable, owing to the difficulty of properly clearing the jet. This is troublesome enough in ordinary laboratory work, but is much worse with a large practical class. Various methods of getting over the difficulty have been tried more or less successfully. I think, however, I have now succeeded in evolving a form of burner which is a considerable improvement on preceding ones.

The improvement consists in replacing the central



jet by a suitably inclined lateral opening in the wall of the burner itself. The burner is left open right through, and the side air holes are done away with. An air regulator can be fitted on the base in the form of a pivoted diaphragm. A simple form of the burner is illustrated in the diagram. This represents a section through the gas supply tube and inlet (to the right of drawing) and one limb of the tripod base (to the left). The upper tube screws into the lower portion. This consists of a very shallow tripod with circular opening for the tube. At one side of the opening is a block into which the gas supply tube is fixed and through which the gas inlet is drilled. The inclination of the inlet and its diameter depend somewhat on the richness of the gas used.

The advantages of the burner are that the gas inlet does not become choked; anything dropping down the tube passes right through to the bench. Further, if the gas inlet is properly arranged, the flame can be turned down very low without its striking back or the air supply requiring regulation. Again, the air regulator fitted on the bottom cannot jam in the way the usual circular regulator does; in fact, it can be com-



THE UMBRELLA BOAT.

pletely removed by the aid of a screwdriver in a few seconds; it is unnecessary except when a luminous flame is desired.

The burner is now in use in Edinburgh and Aberdeen Universities, and works well.

ALTHOUGH there is always a fascination attaching to the invention of a device affecting what might be called the conspicuous and larger needs of mankind, it is probably the improvements on the common articles of daily use that have proved the most profitable to the inventor. As an instance, our attention has lately been drawn to a case of this character, where a device known as the Johnson anti-rattler for thill couplings realized a sale of 1,700 gross in the past six

months in the United States alone, and there was an excellent foreign trade, which indicates that Americans are not alone in appreciating improvements of the smaller kind.

Pennock's Electric Power Transmission Plan.

George B. Pennock, a New York electrical engineer, says he has invented a system of electrical distribution which will revolutionize the present methods of railway transportation. His claim is that he can so distribute electrical energy by means of a new kind of third-rail system that a hundred trains can be moved at a cost no greater than is now necessary to move one train, and that he has practically demonstrated the value of his discovery in electric lighting by supplying sixty standard candle power incandescent lamps with one horse power. The inventor was formerly a train dispatcher on the Pennsylvania Railroad, but for many years has given his entire time to electrical subjects. In an interview published in the New York Sun he says:

"In moving cars by electricity we generate at a central point a certain amount of horse power in the shape of electricity. That must be sent out over the route on which the cars run, and there must be as many times the power required to move one car as there are cars. To achieve the results which I claim will come from my system—that is, not to need a power increased in proportion to the number of cars used—I would build a central station midway between the terminals of the line, and in this I would put a 1,000 horse power engine and a 500 horse power dynamo. That is all that would be necessary to move any number of trains. Then I would put up my voltage distributor, which brings about the required result. This is a circular track cut up into 100 segments each 10 inches long. Mounted on it is an electric motor car of one-half horse power designed to run at a very high speed, to complete the circuit of the track 400 times in a minute. It is locked in by two tracks above, one of which carries the current to run the motor, and the other the current from the 500 horse power dynamo to the distributor.

"Between the rails of the railroad tracks, along their whole length, is placed a series of conducting segments, a brass rail one inch in diameter, each segment 500 feet long, the segments separated from each other by a space of three inches. Running side by side with these segments will be a similar but continuous conductor to complete the circuit. Each of the segments in the distributor is connected with wires to a 500 foot segment between the tracks. When all is ready the motor car on the distributor is set in motion, and, as it flies around the circle at the rate of 400 times a minute, it successively closes the circuit between the small segments in the distributor and the large segments between the tracks, and conveys

to each segment sufficient electricity to start a train. This current is taken up from the large segment into another but smaller voltage distributor on the train, in charge of the motorman. This consists of ten segments, each attached to a motor on the train. The force of the current is 100 volts. The motorman has charge of this, and by turning his switch can use one motor with 100 volts or ten with a thousand. The current will be taken from the segments on the track to the voltage distributor on the trains by means of a connection underneath the car similar to a trolley pole. One of these

trolley wheels or shoes will rest continuously on the continuous rail, so that by generating 500 horse power at the dynamos, distributing it to the segments and putting just enough in each one to start the cars, I can do all the work of the road with 500 horse power. In other words, the same power is intermittently transmitted from one train to another several hundred times a minute. When the cars are started they move on to the next segment, where a new contact is made, thus giving fresh impetus. Finally, I have invented an automatic negative pole stepback to use in connection with the motors on the cars that will multiply the current ten times. [The Editor of the SCIENTIFIC AMERICAN assumes no responsibility whatever for this newspaper story.]

Recent Archaeological News.

Paul Dubois' equestrian statue of Joan of Arc has been set up provisionally in the quadrangle of the Louvre, to see what the effect will be.

Prof. Jakob Burkhardt, the historian and art critic, best known by his famous art guide to Italy, "Der Cicerone," died recently at Basel, his native town, at the age of 79 years.

In the Architectural Record for quarter ending September 30, there is an interesting article by Prof. W. H. Goodyear entitled, "A Discovery of the Entasis in Medieval Italian Architecture." It is accompanied by eighteen illustrations and plans, and, like the rest of the series, is of great interest.

Though the acoustic properties of the Roman theater at Orange have been highly praised, the recent performance by the Comédie Française, before President Faure, of "The Erinnyes" could hardly be heard, as the wind howled through the building. Two great persons, M. Francisque Sarcey and the Duchesse d'Uzès, complained that they had been treated rudely by the officials.

A tapestry map of Warwickshire, Shakespeare's county, 24 feet by 18, and made in 1598, is now on exhibition in London, where it has been sent to be repaired. It is one of five made by Flemish weavers imported into England, and is the largest and most minute topographical record of the time. It once belonged to Horace Walpole, but is now the property of the York Museum.

Dr. W. Flinders Petrie, the Egyptologist, has sent, according to the daily papers, to Dr. Breasod, of the University of Chicago, a valuable collection of relics excavated along the Nile. Among these are statues of Nen Khefa, a wealthy nobleman, and his wife, which are said to be nearly 5,000 years old. They are of limestone and are remarkably well preserved. They will go to the Haskell Oriental Museum of the university.

Prof. Nehring, in describing the domestic animals of the ancient Peruvians, states that the subject is scientifically important, because all the other peoples of ancient America were very poor in this kind of property as compared with the Peruvians and some of the Central American peoples. Nehring examined eighteen dog mummies from old Peruvian graves and ascertained that they belonged to three different races—a shepherd's dog, a dachshund and a bulldog. This discovery is interesting, as it shows the influence of domestication on the formation of races.

Public opinion in Holland is much moved by the sale of three important pictures from the famous Six Collection, the last survivors of those which were formed during the lifetime of the great painters of the seventeenth century. Every art-loving visitor to Amsterdam knows the house where hang Rembrandt's magnificent "Burgomaster Six," and perhaps a hundred other pictures of the highest class. Innumerable attempts have been made at various times to induce the family to sell, but till now without success. At last they have yielded so far as to cede, fortunately not the Rembrandts, but three others—Cuypp's "View on the Maas," the Terburg, and the Gerard Douw. These have lately been sold, after long negotiations, for a prodigious price. It is believed that they have gone to England.


In the will of the late Lady Wallace, her pictures, porcelain, bronzes, artistic furniture, armor, miniatures, snuff boxes and works of art, on the ground and first floors and in the galleries of Hertford House, as well as the Louis XIV balustrade, are bequeathed to the British nation. The bequest does not include personal and modern jewelry, trinkets and effects, nor ordinary modern furniture and chattels, says The Builder. The government in return are to give a site in a central part of London, and build a special museum for the collection. It is also stipulated that Mr. John Murray Scott is to be one of the trustees of the collection. The other trustees appointed by the Treasury are the Earl of Rosebery, Sir Edward B. Malet, Sir John Stirling-Maxwell, Major-General Sir Arthur E. A. Ellis, Mr. A. B. Freeman Mitford and Mr. Alfred C. De Rothschild. Mr. Claude Phillips has been appointed keeper of the collection. The committee appointed to consider how the collection should be housed having recommended the purchase of the interests in Hertford House and its adaptation to a museum, a sum of £80,000 will be obtained for that purpose. No arrangement could be more satisfactory. The character of the Wallace collection would suffer if placed in a new building of a severe character like the National Portrait Gallery. The pictures were specially selected to adorn a private mansion, and it would be difficult to erect one better adapted for their display than the house in Manchester Square. Mr. Waterhouse acknowledged that at first he was not in favor of keeping the collection there, but, on considering the decoration of the rooms and their matchless chimney-pieces, he came to the conclusion that, if the bequest were taken away from its present surroundings, it could never be shown to such advantage. The value of the collection is set down officially, according to the New York Tribune, at the enormous sum of \$22,000,000.

Excavations at Treves.

The excavations that have been going on for months past on a plot of ground belonging to Herr Schabb, a manufacturer at Treves, have resulted in the discovery of a Roman private house, which will excite the interest of antiquaries almost as much as the famous public buildings at Augusta Trevirorum. The front of the house lies parallel with the principal street of the old Roman city. A number of blocks which served as pedestals for the wooden or stone pillars of a portico still remain. The entrance is distinctly recognizable between two buttresses and an immense heap of stones. A long entrance hall running right through the house, from front to back, is intersected by another corridor, so that the gigantic building is divided into four parts. Side corridors lead into the rooms. Of these the marble tessellated bath rooms for hot and cold water and warm air lie side by side, and deserve special mention. The two latter were supplied with warm air through subterranean passages. The escape of the smoke was effected by means of hollow tiles laid on one another. The southwestern rooms have cellars under them. In a light court in the same part of the house there is a well-preserved window, the first ever found in a Roman building. The most interesting thing, however, is the magnificent and richly colored mosaic floor, a rarity of the first order. Experts assign the building to the first half of the fourth century, when Augusta Trevirorum attained the zenith of its splendor under Constantine and his sons.—Public Opinion.

COMBINATION CORNER PIECE.

The accompanying engraving was loaned by the American Carpet and Upholstery Trade, and represents a very neat corner piece. For small drawing rooms,



COMBINATION CORNER PIECE FOR LADY'S APARTMENT.

such as are found in many apartment houses, it is a piece of furniture that might be found very desirable, as it is dainty in design, and occupies but very little space.

Andree's Balloon Expedition.

A telegram from Stockholm, July 27, to the London Times, says that in a letter to the Aftonblad, Dr. Nils Ekholm, who accompanied Herr Andree to Spitzbergen last year with the intention of taking part in his aerial voyage, offers some remarks on the prospects of the expedition based on the full details now received of Herr Andree's ascent. Herr Ekholm declined to go this year because he considered that the impermeability of the balloon was unsatisfactory. In his letter he points out that from the day the balloon was fully inflated it lost 51 cubic meters of gas every 24 hours, representing a diminution in carrying capacity of 56 kilogrammes per day. This, he says, shows that the imperviousness of the balloon had not been essentially increased since last year. Besides this daily escape, various circumstances led to a certain loss of gas in the ascent itself, necessitating a corresponding sacrifice of ballast. After making allowance for these losses of gas, and taking into consideration the fact that in the ascent part of the dragropes were lost and that the balloon at once rose to a height of 15,000 feet to 25,000 feet—which was more than had been reckoned upon—Dr. Ekholm comes to the following conclusions: The longest time for which the balloon would remain in the air would be from 22 to 24 days, and less if mountains exceeding the height attained at the start had to be crossed. As the duration of the projected voyage may be estimated in ordinary conditions as regards wind at 24 days, remarkable good fortune would be necessary for success. Dr. Ekholm declares himself skeptical with regard to the supposed loss of the balloon in the White Sea, but he proposes, nevertheless, that a search expedition should be sent to the White Sea from Vardoe.

Science Notes.

The Brooklyn Institute of Arts and Sciences announces that Dr. Nansen will lecture before that body during the coming season.

A sanitary Bible for the use of courtrooms has just been put on the market, says the Medical Record. It is bound with white celluloid instead of leather, and it can therefore be washed and disinfected from time to time.

The statue of Charles Darwin erected in his native town of Shrewsbury has been placed in front of the school which he attended for nine years. It was recently unveiled and was the gift of the Shropshire Horticultural Society and cost 1,000 guineas.

Andorra, the little republic on the border of France and Spain, is going to give up its picturesque isolation. It now has a telegraph line connecting it with the French system, and a carriage road is being constructed to take the place of the mule track over the Pyrenees, which for ages has been the only means of access to the town.

It is reported, says Science, that the Secretary of Agriculture will ask Congress, at its next session, to authorize the establishment of an agricultural experiment station in Alaska. Suitable scientific experiments would be of great value in showing what agricultural products and domestic animals could be introduced to advantage.

Holborn and Wien have invented a thermo-element composed of iron and "constantan" wire, says the Pharmaceutical Era. This latter is an alloy composed of copper containing 40 per cent of nickel and possesses the peculiarity that its electrical resistance is not influenced by temperature; also, next to the bismuth-antimony element, it is the most sensitive.

The London correspondent of the New York Evening Post cables that Mr. George Murray, keeper of botany in the British Museum, has proceeded to Panama at the instance of the government grant committee of the Royal Society for researches on little known pelagic algæ. During the voyage these organisms will be obtained by pumping sea water through fine silk tow nets.

A committee of the Paris Academy of Sciences, appointed to report on the precautions to be observed in the installation of electric conductors in the neighborhood of powder magazines, concludes that no distinction can be drawn between telephone or telegraph wires and electric lighting mains; that a distance of 10 meters appears sufficient to avoid all risk in the case of underground wires; but for overhead lines a greater distance is advisable—20 meters at least.

Lieut. Keising has lately been lecturing before his comrades in Berlin upon the subject of the value of photography in field operations, says the Army and Navy Journal. He recalls how the Germans employed it in the war before Strasburg and Paris. He is of the opinion that every officer's patrol should have a small hand camera, which should hang at the belt or the saddle, the plates being developed when the patrol rejoins the troops. He advocates also the use of captive balloons for photography.

A Roentgen society has been formed, with Prof. S. P. Thompson as the president, says The Engineer. The intention of the founders is that the society shall occupy a position between those devoted purely to medicine, to physics, or to photography. Some of the members will study the sources of the Roentgen rays, others the applications; some the induction coils, others the tubes and the various forms and adaptations of the apparatus used in the production of the rays. Roentgen photography has been found serviceable in so many branches of scientific investigation that the society appeals to a large constituency for support. It should be the means of increasing the efficiency and applications of the rays, and should also be of assistance to surgeons and others who have entered the new field of work without previous training in physics.

The number of matriculated students attending German universities during the summer semester of 1897 is indicated by the first figures, the whole number of hearers by the second figures, and the number of women among the hearers by the third figures in the following list: Berlin, 4705, 344, 114; Bonn, 1889, 103, 13; Breslau, 1541, 83, 22; Erlangen, 1140, 13; Freiburg, 1449, 95; Giessen, 663, 29; Göttingen, 1123, 72, 34; Greifswald, 834, 19; Halle, 1534, 101, 6; Heidelberg, 1230, 92; Jena, 704, 50; Kiel, 727, 37; Königsberg, 695, 31, 11; Leipsic, 3064, 157; Marburg, 1042, 48, 7; Munich, 3871, 160, 2; Academy of Münster, 487, 10; Rostock, 499, 10; Strassburg, 1016, 31; Tübingen, 1289, 12; Würzburg, 1430, 13. The whole number of matriculated students was 30,982, and hearers 1519, of whom 207 were women; students of theology 4326, of law 8368, medicine 8232, and philosophy 10,006. There was a marked decrease of students of theology and medicine, and an increase of students in the philosophical department, especially in philology and natural science. There seem to have been no women hearing lectures at Leipsic, although there were several in attendance last winter.

The Alaskan Reindeer—the Camel of the North.
BY GEORGE ETHELBERT WALSH.

Since the discovery of large quantities of gold in Alaska and the Klondike excited public attention in this country and Canada, some mention has been made of the reindeer farm established at Port Clarence, on the lower Yukon, and the suggestion comes from Washington that these "camels of the North" could be utilized in carrying freight and the United States mails to the new mining regions. Dr. Sheldon Jackson, whose long residence in Alaska gave him an opportunity to study the needs and condition of the country, first recommended the introduction of the reindeer in the newly acquired territory of the United States, and it was through his representations and urgent appeals that Congress finally, in 1893, appropriated \$15,000 for the new experiment. It was estimated then that it would cost \$500 to import an old reindeer into Alaska from Siberia; but even this apparently large price did not seem too great for the good which the promoters of the scheme expected in return. When Alaska was first purchased from Russia there were many people who claimed that the price was exorbitant, and that the country was a useless piece of waste territory; but in 1893 scientists and practical men of business had begun to think and know differently. The climate was against the development of the territory; but the resources had been found to be tremendous.

The reindeer experiment farm consequently received little opposition from either politicians or private individuals. In fact, it was indorsed by nearly every man of science who had given the question any consideration. The interminable snow fields and stretches of ice could not be traversed by any other animals in the depth of winter, and the reindeer seemed as essential to the development of the country as they have been for ages past to Lapland. The first importation of the animals was small, in order to see if they would thrive in their new quarters. At first everything seemed to go against the experiment; but matters took a turn for the better in the second year. A number of Laplanders were brought over to reside in the new country, to act as keepers and breeders of the animals.

Since then life on the reindeer farm at Port Clarence has been both interesting and profitable. In 1894, when the original herd was reported to be in a thriving condition in their adopted country, the government imported nearly fifty more. The original herd had by this time increased to over one hundred, so that the farm contained about one hundred and fifty reindeer when the revenue cutter Bear left Port Clarence in the summer of 1894.

Hardly any information has been published since then concerning the reindeer. So far as the reading public was concerned, one might never know that reindeer were being raised anywhere within the territory of the United States. Moreover, the Alaskan authorities and people knew little about the experiment, and no accounts were given in the annual reports to Congress about their usefulness. But the animals were thriving in their new quarters, and new importations were being made by the government as the case seemed to demand.

It is therefore with considerable gratification that the news comes from Port Clarence announcing the excellent condition of the reindeer herd. Altogether about five hundred of the animals have been imported from Siberia by the government, and these have increased in the natural manner to over one thousand. The animals take naturally to the country, and find ample food in the reindeer moss which thrives throughout the great Alaskan snow fields. This moss is so abundant that it is estimated that millions of reindeer could exist on it, while almost any other animal would starve or freeze to death. The reindeer on the farm have not only been bred for future usefulness, but they have been trained to carry loads, and every full grown animal has been broken to harness by their Lapland keepers.

In a short time the full herd will probably be needed to accommodate the gold seekers who are now flocking to the Klondike. It is announced semi-officially that the government will establish next summer a reindeer express service from Bering Strait to Katiak Island, where the steamers which sail for Sitka touch. A new station or farm for the reindeer will also probably be established somewhere on the upper Yukon, within easy reaching distance of the new gold fields. It is believed that these animals will prove more serviceable than either dogs or a railroad in carrying small loads and the mails from the placer mines of the Klondike to civilization. Mongrel dogs in Alaska cost from \$100 to \$200 apiece; but a trained reindeer is worth a whole pack of such animals for carrying loads.

The reindeer require little or no care if properly handled. In Siberia and Norwegian Lapland the work of rearing them is a profitable industry. There is a disease similar to the rinderpest in cattle which occasionally attacks and carries off whole herds; but, when free from this pest, the herd is almost sure to double itself in numbers year by year. So long as the reindeer moss flourishes, the deer will have ample

nourishment, and the owners have only to supply them with shelter.

In return for this simple care the animals transport the burdens of the keepers across the country at a most remarkable speed and in the face of every discouragement. In the palace at Drotninghold, Sweden, there is preserved the portrait of a reindeer who is said to have accomplished six hundred miles in forty-eight hours, drawing a bearer of dispatches. This remarkable feat may not be susceptible of proof, but it furnishes us with an approximate idea of the speed and endurance of the animals.

Besides serving as good horses, the reindeer are extremely valuable to inhabitants of Arctic climates in other ways. The does yield nearly a pint of milk a day, which is so rich that it is almost wholly cream, and it will stand a good deal of water before it becomes inferior to our best cow's milk. This milk is of great nourishing and refreshing value in the winter season, and is eagerly sought after by those forced to live in such cold regions. A herd of several hundred reindeer can furnish milk for a good size town or mining camp. The Lapps, of Norwegian Lapland, make a cheese or skier out of the milk, which is also a very desirable article of diet in winter.

When dead, the reindeer's services to man do not cease. The blood is drunk warm, and every part of the body utilized in some way. The flesh is dried or smoked, in which condition it can be kept indefinitely in such a climate. The surplus blood is preserved by freezing, and is then used for puddings, and the stomach and contents are frozen for special delicacies. The Lapps make bow strings and a rough thread out of the sinews and intestines, and glue from the hoofs, and various articles of use and ornament out of the antlers. But more important than any of these are the blankets and clothing which the skins of the reindeer yield. There is no skin of any wild animal that surpasses that of the reindeer for keeping out the severities of an Arctic winter. A single skin wrapped around the body of a man enables him to withstand the rigors of a climate as intense as any that prevails in the Klondike. On the coldest Arctic night the Lapp and Samojede find comfort and pleasure under the protecting covers of their reindeer clothing and blankets. The same skins are utilized for mufflers and gloves. In Russia the skins of new-born fawns are in special demand for glove making.

The ease with which the reindeer traverse marshy tundras, swim ice-cold streams of water, and pass across fields of soft snow, has made them special objects of wonder to all travelers in the cold northern countries of Europe. The singular foot conformation of the animal is probably the most interesting part of the reindeer, for it is owing to this that it is enabled to perform feats that defy all other animals. Besides crossing crusted snows, icy lakes, and marshy tundras with the greatest facility, the reindeer can scale icy precipices that would baffle almost any other creature, and all of this is done with perfect safety both to the animal and the load that it drags behind.

The foot of the reindeer is cloven in the middle, and each half is turned up in front. These two sections of the foot are greatly elongated, and capable of great lateral expansion. When the foot is placed on the ground the two sections expand three or four inches, and when it is raised again a muscular contraction brings the two digits together with a loud clattering noise. It is this peculiar sound which one hears half a mile away when the reindeer are approaching. Secondary hoofs that are not developed in other deer are greatly prolonged in the reindeer, and having a slight backward inclination, they add valuable support to the animal. Thus, with such a peculiar foot conformation, the reindeer secures a good foothold on any solid substance, and performs wonders of strength and agility within the Arctic circle where all other animals are placed at a disadvantage.

What Constitutes Negligence.

Is it negligence to step off the pavement in a street without looking to the right to see if the way is clear on the near side? The London Law Journal makes the above query and then adds: Formerly a pedestrian might with tolerable safety have trusted to his ears to find out if there was any vehicle close to him, but now that the bicyclist is ubiquitous, common prudence suggests that for his own security a foot passenger should look in both directions before he crosses the road. The safety of the bicyclist does not count with the majority of non-riders. He is not altogether unreasonably regarded as a nuisance where there is much traffic; yet he is entitled to pursue his way along a thoroughfare, and in regard to him the foot passenger has duties as well as rights. In a case which was before the court of appeal recently the facts were that a butcher's boy with a knife in his hand stepped suddenly off the narrow pavement of a street without even a glance to the right, and came at once into collision with a bicyclist, who, as the jury found, was riding along carefully and at a reasonable speed. The result was that one of the unfortunate rider's hands was struck by the knife and seriously

hurt, and he brought an action to recover damages for his injuries. The jury found that the occurrence was a "pure accident," and the court were unanimous in saying that they would have come to the same conclusion. It seems to us, however, that the jury would have been justified in finding that the butcher's boy, who admitted that if he had looked he would have seen the bicyclist, and waited for him to pass, was guilty of negligence. On the other hand, it may be that a street is so narrow or so crowded that a bicyclist is not justified in riding through it, or that he ought, at any rate, to ring his bell continuously, irritating though the tinkling may be to himself or to the people within earshot. These points, however, are wisely left for the determination of a jury.

The Sleep of Plants.

Like animals, all plants require intervals of repose, during which the vital functions are slowed down and the organic structures undergo repair. Some plants repose during the rainy season, others during periods of drought, but while some plants sleep during the cold or the comparatively cold season of the year, others again take their rest when the average temperature is high. It occurred to a Norwegian observer to investigate the sleep of plants, more particularly with the object of shortening the period of repose, and this he claims to have attained by subjecting the bulbs or buds to the action of chloroform vapor. He asserts, indeed, that plants thus treated subsequently develop more rapidly than those whose repose has not been intensified by the narcotic action of this drug, and the observation is not without considerable interest.

If his observations are trustworthy, it follows that sleep in plants is not strictly comparable to that of animal life, for we do not suppose that the period allotted to sleep by animals could advantageously be shortened by the administration of an anæsthetic. Sleep, on the other hand, is a relative rather than an absolute condition. Its value as a restorative depends in a very marked degree on its intensity, and certain individuals derive more benefit and recuperate their jaded energies more effectually in five or six hours than others do after twice as long. This recuperative energy is asserted to be an indication of a high standard of vitality, and common observation certainly lends color to the view that diminished recuperative power is indicative of physiological deterioration.—London Medical Press.

Pasteurizing Milk at Home.

Milk has been pasteurized successfully, according to the American Agriculturist, by taking any ordinary bottles, filling with milk to the neck or a little below, placing a stopper of cotton batting in the neck, then setting on a thin strip of wood, or inverted pie plate, which has been perforated, in a thin basin or pail of water. The whole is then heated until the milk shows a temperature of nearly 150°. The bottle is then stoppered and the pail and contents are removed to the back of the stove, where the temperature will remain fairly constant for twenty minutes, especially if covered with some non-conducting material, as a cloth or dry towel or the pail cover. At the end of the twenty minutes the bottles are removed and set in warm water, which is gradually cooled and then iced. The bottle may finally be put in the refrigerator after being partially chilled in water.

Pasteurizing may also be accomplished with equally good, if not better, results in tin vessels, either a double boiler oatmeal cooker or two dishes of suitable capacity, one with a diameter two inches shorter than the other. The water is poured into the outer dish at boiling point, the milk dish and contents being set in at once and the milk constantly stirred until its temperature is 150°. It is then removed for a moment, while the water in the outer dish is tempered to the same or a degree or two higher. The milk is then set back into the boiler, put to one side and closely covered and wrapped, in order to retain the heat for fifteen or twenty minutes. The advantage of tin vessels is that they may be plunged from hot water to ice water without danger of breakage, and with possible advantage to the milk.

If the object of pasteurizing be to destroy the bacillus of tuberculosis, a minimum temperature of 149° should be maintained for fifteen minutes, or 140° for half an hour.

If milk can be got from a herd known to be free from tuberculosis, or the person has no fear of this trouble, a pasteurizing temperature of from 133° to 140° maintained for fifteen or twenty minutes is sufficient to give good keeping qualities and to effectually get rid of 95 per cent of all bacteria, including the forms which produce stomach disturbances, vomiting, and cholera infantum in children.

In all pasteurizing work the sudden chilling of 50° or thereabout is imperative. The milk should be kept covered and at as low a temperature as can be obtained. Treated in this manner, pasteurized milk will be found to have a delightfully sweet, pure taste long after common milk has lost its freshness. On the average it keeps from six to thirty-six hours longer than unpasteurized milk in the same temperature.

THE HEILMANN ELECTRIC LOCOMOTIVE.

It is now some three years since Mr. J. J. Heilmann, of Paris, designed and placed in operation his first standard gage electric locomotive, which was known as La Fusee Electrique and was tested upon the lines of the Compagnie des Chemins de Fer de l'Ouest, of France. The Fusee was of 600 horse power and 120 tons weight and it was designed for hauling the ordinary class of passenger trains. The novelty of this locomotive consisted in the fact that it did not take its current from a feeder connecting with a distant power station, but carried its power station with it—the boiler, engine, generators, and motors being all combined in one machine upon one set of wheels and comprising an absolutely self-contained electric locomotive.

In spite of a vast amount of adverse criticism based on theoretical *a priori* grounds the builders of the Fusee were so well satisfied with its performance that they have constructed two more locomotives of the same type, but having much greater power and embodying the improvements suggested by the trials above referred to. By the courtesy of the builders we present a series of views of the first of these engines taken during its construction at the shops.

The designs of the Heilmann locomotive have been subjected to considerable criticism, mainly on the ground that it is at an evident disadvantage compared with the ordinary steam locomotive, because it necessitates an extra conversion of power, with its inevitable attendant loss. But while the loss in conversion is admitted, it is claimed by Mr. Heilmann that there are valuable compensations to be realized. In the first place, the absence of reciprocating parts and counterbalance weights secures a perfectly balanced engine which is easy upon the track and bridges. There is a further economy, it is contended, in the use of a many-cylindrical high speed engine, and although considered as an electric motor, there is a greater weight of machinery to be carried than in a motor driven from a central station, this is offset by the absence of any loss by transmission over a line of greater or less length.

Regarding the first claim that this type of locomotive is perfectly balanced there can be no dispute, and the designer is entitled to full credit for having solved one of the most difficult problems connected with high speed locomotives. In the ordinary type the evil effects of "excess balance" are met or mitigated by the use of large driving wheels. This, however, necessitates a slow piston speed and a corresponding reduction of the indicated horse power. In the Heilmann machine the main engine is completely balanced by the arrangement of the six cranks, and the tests which have taken place show that there is a complete absence of the well known hammering and plunging effects noticeable in the ordinary locomotive.

It will be argued that the ordinary electric motor is also balanced, and that the extra load of boiler, engines and generator are a distinct handicap to this engine. To this it must be answered that in a locomotive of 1,350 horse power, which it is claimed the new machines will develop, the load of boiler, engines, etc., is almost necessary to give the requisite adhesion

out undertaking the great expense which will be entailed in the use of the central station system.

The machine is built upon a pair of deep plate girders and carried by a couple of eight-wheel trucks, one under each end. The total length of the engine over all is 61 feet and the rigid wheel base measures 37 feet 3 inches. The front of the engine is not, as one would suppose from looking at the engraving, the end occupied by the boiler, the latter being placed over the rear trucks, the forward half of the platform carrying the engines, generators, exciters, etc. Water is carried in two tanks, one on each side of the boiler, and the coal bunkers are situated just ahead of the tanks and on each side of the fire box. The engines, generators, etc., are completely housed in by a large plate steel cab or




Fig. 5.—CROSS SECTION THROUGH MOTOR—HEILMANN LOCOMOTIVE.

casing which is given a sharp plow-like form at its forward end with a view to reducing the air resistance.

The boiler of the first experimental locomotive was of the Lentz type, with corrugated fire box and combustion chambers, but in the present type the designer has returned to the ordinary locomotive style of boiler, the fire boxes being, however, of copper and built on the Belpaire pattern. There are 351 tubes 1.77 inch in diameter and 12.5 feet long, and there are 35.95 square feet of grate surface, the total heating surface of the whole boiler being 1,996.5 square feet. The boiler pressure is 200 pounds to the square inch. The generators are driven by a Willans compound six-crank vertical engine, the cranks being set at 0°, 120°, 240°, 240°, 120° and 0°, by which arrangement the difficulties of counterbalancing are completely overcome. In spite of its high speed, the engine runs in perfect equilibrium. As we have said, this is one respect in which Mr. Heilmann claims a distinct advantage over the ordinary form of locomotive, in which the well known counterbalance problem is causing no end of trouble and expense.

There are two continuous current generators directly connected to the main shaft, one at each end of the engine. The generators, which were built by Messrs. Brown, Boderi & Company, are continuous machines coupled in parallel, and each has a capacity of about 1,000 amperes at 450 volts. They are excited by a small four-pole self-exciting dynamo which is driven by a simple Willans engine of about 28 horse power. The current is led to eight motors, one for each axle of the trucks. The motors have four poles, with two field

There is an eight-way switch for reversing the current in the armatures of the motors and for instantaneously changing their direction. The speed may be varied by means of a rheostat placed in the exciting circuit of the generators.

The controlling gear is arranged in duplicate, one set being placed at the forward end of the locomotive and the other near the boiler in the position usually occupied by the throttle and reversing lever in an ordinary locomotive. This is done to enable the engine to run in either direction. It is claimed by the makers that these locomotives will take a train of nearly 400 tons at a speed of 62 miles an hour. We are informed that the preliminary trials, of which we do not as yet possess the details, give reason to expect that when they are in active service these locomotives will be capable of performing the full duty for which they are designed.

The Scientific American in Russia.

The following is a letter of G. Wilfred Pearce to the editor of the New York Sun. It gives some interesting particulars about the state of trade in Russia and incidentally bears witness to the appreciation of the SCIENTIFIC AMERICAN in that country:

Sir: Several mechanical engineers and manufacturers of machinery which find markets in Europe, Asia and Africa, who have had opportunities for conversing with Major Moses P. Handy, commissioner to the Paris Exposition of 1900, are of the opinion that the 500,000 square feet of space which Major Handy has applied for will be quickly taken up by American

manufacturers, who are keenly alive to the fact that the exposition will be open sesame to a large and profitable trade in certain lines of manufactures in metals in which we can control the markets of the world.

Russian merchants who do business in our city [New York] are saying that nearly every merchant, engineer and manufacturer in Russia will visit Paris during the exposition year, by which time business will be lively all along the line of the great Transsiberian Railway, which is destined to play a great part in the commerce of Europe and Asia. At the present time the European and Asiatic demand for American machinery and agricultural implements is very great. In electrical and steam apparatus our makers are driving a lively trade with Russia.

During this week I have seen a letter from a large firm having warehouses in St. Petersburg and Moscow, inquiring as to the reliability of the Richmond Locomotive Works, whose advertisement the Russian says he saw in the Sun. The concern wants about \$100,000 worth of apparatus, which it could not get at the Samavar Locomotive Works, owing to the rush of orders at that new plant, equipped with American machinery. St. Petersburg is in the market for more than \$1,000,000 worth of apparatus. The imperial engineer, who gave me the data for the proposed electric lighting plant at St. Petersburg, informs me that he reads the Sun and SCIENTIFIC AMERICAN, in order to "keep up with the march of Father Time."

Electrical Cabs in London.

In London a company has placed a dozen electrical cabs in the streets. They resemble coupes, and the ac-




Fig. 6.—PLAN OF THE HEILMANN LOCOMOTIVE SHOWING ARRANGEMENT OF BOILER ENGINES AND GENERATORS.

when the locomotive is working up to full power, as in starting or on a steep grade. It is evident that in proportion as the weight of the steam boiler, engines and generators become necessary for adhesion, the advantages of their installation in a separate power house disappear.

The above facts show that the design is per se not so altogether indefensible as many of its critics have roundly declared; and the aims of its designers appear yet more reasonable when they state that in building the Heilmann locomotive an effort is being made to make it possible to equip the trunk railroads electrically, without making any radical changes in the road itself. With this fact in view, it must be admitted that whether the arguments above given are sound or not, this machine will enable the railroad companies to experiment with electric traction on a limited scale with-

cores placed horizontally. The field winding is an insulated copper strip and the armature is a toothed drum wound in series and mounted on a hollow steel shaft which carries at one end a disk. This disk transfers the motion to the axle by means of three powerful links which are carried upon three corresponding pairs of springs secured between the arms of one wheel. The arrangement is shown in Figs. 3 and 5 in the accompanying illustrations. The axle passes with sufficient clearance through the hollow shaft, and the springs have sufficient flexibility, even under the full power of the motor, to allow free movement of the hollow shaft. The motors are all connected in parallel and each motor is fed by a special circuit from the switchboard and has its own switch and automatic cut-out. For low speed and under heavy loads the motors may be grouped in a series of four by means of a controller.

accumulators consist of forty cells, capable of propelling them over fifty miles, at a cost of fifty cents. The rear wheels do the driving and the front wheels do the steering. They have heavy rubber tires and upholstered spring cushions, are lighted by electricity, are speedy, and almost noiseless. They appear to be giving every satisfaction. The machines seem under perfect control, and thread their way wonderfully through the traffic. The tariff is the same as that of the cabs. They look like a cross between a brougham and a four-wheeler, with accumulators underneath.

The French used the bicycle in 1871, during the siege of Belfort, for carrying dispatches. The wheel adopted at that time was of course the "ordinary" or high wheel. This was the earliest introduction of the cycle in the army.—Stahl und Eisen.

HOUSE BUILDING BY RITUAL.

BY COSMOS MINDELEFF.

The man who builds a home, be he white or red, appears to be the special target of all kinds of trouble and annoyance; but in the latter case, that is to the red man, there are certain requirements which make the task even more onerous, while on the other hand there are compensating advantages. The pueblo tribes of Arizona and New Mexico, alone of all the Indians, build permanent stone houses, quite equal to those of white settlers in that country, and they have developed a peculiar system of building of their own which is of interest to every house builder.

The pueblo Indians now number about ten thousand souls, living in thirty villages, principally along the Rio Grande in New Mexico, and several distinct languages are found among them, but their house structures are essentially the same throughout. The largest of the villages, the pueblo of Zuni, which has a population of sixteen hundred, has been often visited, and the seven villages of the Moki, in northern Arizona, are also becoming known through the periodical performance there of the celebrated snake dance. Both of these groups have been studied for some years by the assistants of the Bureau of Ethnology, and the results of their work are now being published.

The houses of these people consist of groups of rectangular rooms, built of selected stone, or in recent

end, or in an adjoining row, rooms are abandoned and going to decay. This odd condition misled the early explorers, who reported that the tribes were rapidly becoming extinct, whereas they are holding their own or increasing slightly in numbers.

The clans, which are great artificial families, all the members of which claim descent from some mythical common ancestor, are themselves subject to change from the same social conditions. Some grow and increase in size, while others wane and eventually become extinct. Thus in the Corn clan there are groups which claim to be of the stalk, leaves, grain, pollen, etc., and should the clan prosper, each of these subdivisions will develop into a full-fledged clan. It all depends on the number of girl children who are born into the clan.

In one of the Moki villages there is a little cluster of four or five rooms standing separate and apart from all other houses. It is the home of the remnant of the Butterfly people, now consisting only of an old woman and her young daughter, besides two sons. As the sons will eventually marry and go elsewhere to live, the future of the clan depends entirely on the young girl. Should she live to marry and have many girl children, it is quite within the possibilities that the Butterfly clan may spread out and cover the whole village; but should she die unmarried, the clan will become extinct, the house will be abandoned, and in a few years its site will be marked only by a few heaps

the walls, beams for the roof, clay for mortar, etc. As the villages of the Moki are all situated on the tops of the mesas, 600 feet or more above the valley, this is no small task.

When everything is in readiness, announcement is made from the housetops by a crier, for the building of a house is a social function participated in by the friends and relatives of the woman who is to build. As the women own the houses and exercise absolute control over them, they are also the builders. There is always a man or two about, however, to do the heavy work. This duty is generally assigned to some of the male members of the family, and is not always willingly performed.

The chief of the village provides four eagle feathers, with a short cotton string tied to the stem of each. These are sprinkled with sacred meal, and prayers are breathed upon them for the welfare of the proposed house and its occupants, and that the walls may take a firm hold of the ground. The feathers are called *nakwa-kwoshi*, meaning a breathed prayer, and the prayers are addressed to *Masauwu* (the sun) and other deities concerned in house life.

The feathers are placed at the four corners of the house and a large stone is placed over each one. The place where the door is to be is marked by bits of food placed on each side of it, with prayers that there may always be plenty of food within. The lines to be oc-



PUEBLO HOUSE BUILDING BY RITUAL

years of adobe brick dried in the sun but not baked. The rooms are arranged in connected rows or clusters. Some of the latter are of huge size, resembling in appearance a gigantic hive and containing several hundred separate chambers. These were at first supposed to be communal structures, but it is now known that while each cluster is the home of a certain clan or combination of clans, the different families who compose it each have their own quarters in it.

The clustering of rooms into huge hivelike structures grows directly out of certain rules of house building, which are the result of peculiar social conditions under which the people live. Among them descent is in the female line; the children of a marriage belong to the mother and are members of her clan and of her family. As a man is not allowed to marry within his own clan, he loses some of his rights when he takes to himself a helpmate, or more correctly when his helpmate takes him, for when he marries he goes to the home of his wife to live, and to a certain degree is adopted into her family.

From this it comes about that families in which there are many girls must necessarily increase and spread out over more area, while those in which the children are all boys become extinct in the second generation. But as the house cluster is the home of the clan, when it becomes necessary to erect additional rooms they are invariably added to and connected with those already occupied, and it is not unusual to see houses in course of construction at one end of a row while at the other

of stone, for it is the custom under such circumstances for the relatives of the family to tear down the house and re-employ the material.

The position of the women in the tribe is all that any of them could ask. They do no field labor, other than assisting in the harvest, and are free to devote their whole time and energy to their domestic duties and the care of their children. In the house their sway is absolute and undisputed. The crops in the field are considered the property of the man of the house and he is required to work them; but when they are garnered and brought in they become the property of the woman, who is also the sole owner of the house in which they are stored. The status of the husband is merely that of an honored guest, and should he misbehave in any way, he can be sent back to his family or turned adrift to shift for himself. It is hardly necessary to add that the greatest affection prevails in the household, and that such a thing as wife beating or ill treatment of women is unheard of in the tribe.

When a family finds it necessary to build additional rooms, notice is sent to the priestess of the clan, who makes the necessary arrangements. This priestess is the social head of the clan, and no business connected with the house can be conducted without her aid. She has also the final say in all proposed marriages, etc. The men of the family are required to bring in the necessary material; broken and dressed stone for

cupied by the walls are then marked by passing around the site from right to left, scattering on the ground particles of bread and other food mixed with native tobacco. This ceremony is accompanied by a song to the sun couched in archaic terms, the meaning of which the people have now forgotten.

After this ceremony, the women proceed to lay up the stones in the walls, the heavier ones being lifted into place by the men, who are there for that purpose. Mud mortar, from a pile nearby previously prepared, is used sparingly, and the stones are laid in it in irregular courses. When the walls reach a height of 7 or 8 feet the top is brought to a fair level and the roof beams are put in place.

The roof beams are often brought from great distances, as suitable timber does not grow near the villages. In the Moki traditions it is stated that the beams for the mission buildings erected for the monks in the early part of the seventeenth century were brought on the backs of men from the San Francisco Mountains, a distance of more than a hundred miles. Although the missions were destroyed in the insurrection of 1680, and never rebuilt, some of these old beams were used in other structures, and still can be seen there.

Above the main roof beams, which are about two feet apart, there is another series of lighter poles placed across them. Over these a layer of reeds or twigs is placed, and over this grass and brush. A layer of mud is then spread over all, and being covered with dry

earth, is trodden down firmly. The women do all this work, and when it is finished, a floor is made inside with a thick coating of mud, trodden down in the same way; in fact, roofs and floors are much the same, and in the upper stories the floors of the rooms were once the roofs of those below. When the floors are done, the walls are plastered with mud, nicely smoothed with the hand. Sometimes they are finished with a wash of white clay, which gives them a very neat appearance. Formerly a custom prevailed of leaving a small space on the wall bare, a belief existing that one of the gods came and finished it; and although the space remained bare, it was supposed to be covered with an invisible plaster.

When the house is completed to this point, four feathers are prepared, similar to those used under the four corners of the house. These are tied to a short willow stick which is inserted over one of the central roof beams. The feathers are renewed every year at the feast celebrated in December, when the sun begins to return northward; that is, at the winter solstice.

The ceremony known as "feeding the house" is then performed. This is an offering to the sun, and consists of placing bits of food among the rafters, with prayers to the sun that he may smile upon the occupants of the house and not hasten the departure of any of them to the other world. After this, the women build a fireplace in one corner of the room under a hole left in the roof, and construct over it a chimney hood to confine the smoke to the proper exit. A binlike arrangement, or stone trough, is built in another corner, and three flat stones are mounted in it for grinding corn. The house is then ready for occupancy. The door is merely an opening, closed by hanging a blanket over it when necessary, and windows are merely holes left in the walls when they were constructed. In the cold winter weather these are closed by stone slabs, or built up solid with masonry, the filling being removed again in the spring.

The Mummy of a Pharaoh.

The greatest discovery of mummies ever made in Egypt, says Public Opinion, was in the year 1881, when the remains of thirty-nine royal personages were brought to light at Deir-el-Bahari, Thebes. One of these was proved to be the mummy of King Rameses II, the third king of the ninth dynasty and the Pharaoh of the Jewish captivity. This mummy was in a perfect state of preservation. The mummy case itself was of sycamore wood, plain and unvarnished, and without a spot or stripe of paint, something reckoned as unusual. The case was, however, carved to represent Rameses in the position of Osiris. The crossed arms rested upon the breast. In the right hand was the royal whip and in the left the royal book. The features were most delicately carved in the soft wood, and the whole was surmounted with the crown of Upper and Lower Egypt and surrounded by a carved representation of the uræus serpent. The name of Rameses was written in plain black characters upon the case, which bore no other text or representation whatever, strongly contrasting with the exaggerated dedications noted on almost all the other cases found in the same pit. The mummy itself was carefully wrapped in rose-colored and yellow linen of a texture finer than the very finest Indian muslin. In the different folds of this linen several dried lotus flowers and leaves were found. In the folds of one of the bands which passed across the grave clothes to keep them in shape was a folded papyrus bearing inscriptions which informed the reader that this, the mummy of Rameses II, was concealed in the pit where it was found at a time when a foreign army invaded Egypt. This quaint bit of information, which was probably written two thousand or two thousand five hundred years ago, is as plain as though it had been penned but yesterday.

A Nebraska International Exposition, 1898.

Congress has adopted a resolution to the effect that the President be authorized, if in his judgment it would not be incompatible with the public policy, to invite foreign nations to make exhibits at the Transmississippi and International Exposition to be held at Omaha, Neb., between June 1 and November 1, 1898. Congress has already recognized the Omaha exposition to the extent of appropriating \$200,000 for a government department and exhibit. The States in the neighborhood of the Mississippi River district are making special preparations too, and Iowa, at the last session of the Legislature, made a preliminary appropriation. California is another of the States which is to take part, and Louisiana, by act of Legislature, has intrusted to the State board of agriculture the business of providing for a fitting display of Louisiana's products. The purpose of the Omaha exhibition is primarily to show "the products, resources, industry and civilization of the States and Territories west of the Mississippi," embracing, it is said, two-thirds of the area, one-third of the population, and one-half of the wealth of the United States. The Transmississippi and International Exposition is a corporation organized under the laws of Nebraska with a capital stock of \$1,000,000.

The Field of Landscape Art.

We are constantly asked whether the profession of landscape gardening offers a promising field for young men who are looking for some calling in life which will be useful and remunerative. We have always felt obliged to reply that there is comparatively small demand for the counsel of landscape gardeners in this country, and we have added that until the true functions of these artists are more thoroughly recognized the call for their professional services will be limited. Most of the men who make inquiries on this point have themselves hazy notions as to what the legitimate field of a landscape gardener is. The prevalent idea is that his work is chiefly ornamental, and that his province is to do about the same thing for the surroundings of a house that the decorative artist does for its interior when he selects the furniture, rugs and hangings and decides upon color schemes and the like. That is, after an architect has built a house, it is considered proper to call in a landscape gardener to plant some ornamental trees and shrubs about it and lay out paths and flower beds in order to beautify the grounds. Now, it is true that the landscape gardener, like other artists, has to deal with beauty, but his first and fundamental study is to provide for human use, for comfort and for convenience. An architect of taste does not make a building and then hang ornaments upon it without and within. His structures will be beautiful, but this beauty is developed out of the design so as to be an essential part of it, and this is so profoundly true that the best architectural work will be beautiful primarily because it serves the purpose for which it was created. The same rule should hold in regard to the development of the grounds about a house. These should be primarily laid out for use and convenience, and their beauty should grow out of their perfect adaptation to the wants of those who are to use them. In short, as we have said a great many times, the house and grounds should be planned together, so as to make one picture; but, even beyond this, they should have a unity of design which is more than superficial. In fact, the beauty of the scene, which includes both the house and the grounds, should grow up from the general design and framework of the house and grounds, as a place where all the varied necessities of the family in the way of health and happiness and home life are the first things considered. This is the reason why no ready-made house plan is adapted to all sorts of ground and why any ready-made planting plan is not available for use with all sorts of houses.

The most hopeful symptom we know is that architects are inquiring more and more for competent designers in landscape to assist them. That is, they feel the need of advice from some one who is trained to the planning and modeling of ground, one who is skilled to see at once all the possibilities that lie in any situation, not only for appearance but for use; one who knows how to take advantage of any diversities of surface or differences of outlook so as to make them available for varied purposes. Such a man can be of assistance to an architect, not only in locating the house in such a way that it will appear to the best advantage, but also for placing it where the principal rooms will have a pleasing outlook. He will contrive facilities for access to it and agreeable lines of approach. The arrangement of different parts of the grounds for special uses requires thought and experience which are outside of the ordinary lines of the architect's study, and therefore the best architects have learned that the highest service which a landscape gardener can render is precisely at the point where the essentials of the combined design of house and grounds are being considered.

All this means that a landscape gardener ought to be much more than a mere decorative planter. The successful designing of public parks or of private grounds for daily occupation means first of all the study of human wants—the necessities of men and women and children of various circumstances and conditions. A good artist must be primarily a man of sound judgment, and he should have cultivated mind, wide sympathies and catholic tastes. Reading and travel and scholarship can do for the designer in landscape all that they can accomplish for the architect. A man may be able to mass a shrubbery effectively or arrange a border of herbaceous plants with skill and yet not have a particle of that profounder art which was seen in the grouping of the great buildings at the Columbian Exposition and the planning of that Court of Honor which was the crowning artistic success of Mr. Olmsted's life. This view of the case contemplates an ideal that is rarely attained, and it is because the work of real artists in this line is rarely seen and still more rarely appreciated that the very existence of such an art is practically ignored or denied. If city park boards realized what a trained park maker is capable of creating out of a given piece of ground, they would never content themselves with asking an engineer or surveyor or mere gardener to design a public pleasure ground. We ought to have reached a stage of civilization when it is no longer believed that any unskilled journeyman is competent to lay out a park or garden, or pass judgment on the plans of a park or garden. If any artist needs sound judgment,

united with taste and training, it is the man who studies public and private grounds and prepares them for the use and enjoyment of man.—Garden and Forest.

How Fire Causes Death.

A writer in the Hospital says: Those who lose their lives in conflagrations do not by any means always suffer physical pain. In many cases, no doubt, sharp terror is the one thing of which the victim is conscious, and in many more, strange as it may seem, consciousness plays no part, life ceasing painlessly and without a struggle.

In great conflagrations gases are produced which have much the same effect [as chloroform or similar anesthetics], and it is a fact that of those who lose their lives in such catastrophes a considerable proportion pass into death without any evidence of having suffered. This result is produced especially when a fire has smoldered, when the access of air has at first been insufficient to cause complete combustion, and when that deadly gas, carbonic oxide, has sent its victims into lethal sleep before the actual flames have reached them.

Of those, however, who have evidently struggled and fought, and whose charred corpses are afterward found in attitudes suggestive of violent efforts made in attempting to escape, it must not be imagined that they have of necessity been burned alive and have died in the agony which such contortions are popularly imagined to express.

Death from agony is really death from shock, a condition in which the body is limp and helpless; whereas in death from suffocation struggling may go on even after consciousness has passed, and the strained attitude of the corpse may be expressive only of the final paroxysmal effort made in a state of entire unconsciousness.

Suffocation in a fire depends on something more than mere carbonic acid poisoning. It is the stoppage of the breathing by the stifling vapors which does the mischief. Carbonic acid would doubtless kill if it could be breathed, but any one who has attempted to enter a burning building will know that suffocation depends, not on the stuff one breathes, but on the fact that one cannot breathe at all. The lungs are as much deprived of their supply of oxygen as if the sufferer were plunged over head in water, and the struggle produced is much the same.

While then we must admit the horror of the moment, the terror, the fight for breath, and finally the death from suffocation, we must remember that all this is often a matter of short duration, and that it is something very different from the slow torture of being burned alive.

The writer reminds us that, owing also to the excitement of the moment, the body of one who is in a great fire is probably insensible to pain, just as it often is in battle. He says:

The instances are so frequent in which more or less severe and painful wounds have only been discovered after the necessity for action had passed away that we are driven to hope and to believe that, so long as all the energies are absorbed in the effort to escape, actual suffering, even from fire, may not be great—may even be unfelt.

Yet there is another, and not so comforting, side to the picture. Says the writer:

It must be recognized that, while all this is true, there are cases in which people are actually burned alive—consumed little by little until the heart stops from shock.

Familiar pictures of martyrs at the stake show us one of the conditions for such an event; the wind driving the smoke aside so that the head, the brain, and thus the consciousness, are left intact until the heart is stopped by sheer agony.

It must always be remembered that no one can live or retain consciousness when actually within the flames. But those who are caught and held fast in the full blast of fresh air which is being drawn into the center of the conflagration cannot be suffocated, they cannot make those violent efforts which would numb their consciousness of pain; they can but wait and suffer until, as the result of agony or terror, let us hope the latter, their hearts stand still. This is indeed a terrible fate.

Be Good to Yourself.

The Medical and Surgical Reporter gives the following practical advice: "Think deliberately of the house you live in—your body. Make up your mind firmly not to abuse it. Eat nothing that will hurt it. Wear nothing that distorts or pains it. Do not overload it with victuals or drink or work. Give yourself regular and abundant sleep. Keep your body warmly clad. Do not take cold; guard yourself against it. If you feel the first symptoms, give yourself heroic treatment. Get into a fine glow of heat by exercise. This is the only body you will have in this world. Study deeply and diligently the structure of it, the laws that govern it, the pains and penalty that will surely follow a violation of every law of life and health."

FIRING A TORPEDO.

The accompanying illustration of a torpedo in its flight from the ship to the water must certainly be reckoned as one of the curiosities of photography. It was taken during the recent naval maneuvers in Great Britain, and it represents the position assumed by the torpedo just after it has left the firing or launching tube.

As our readers are doubtless aware, the Whitehead torpedo is nothing more nor less than an air-propelled cigar-shaped little ship, carrying its own air chambers amidships, its propelling engines in the stern and the deadly charge of guncotton in the bow. When a warship goes into action she carries several of these torpedoes ready charged with guncotton and compressed air. When she is within striking distance of the enemy, one of them is placed in the launching tube, a long cylinder of metal of approximately the same internal diameter as the external diameter of the torpedo, and when the object is within range a small charge of powder or compressed air serves to eject the torpedo in just the same way as a shell is fired from a gun. The discharge of the torpedo starts the propeller engines, which continue to drive the torpedo after it has entered the water.

Before it is fired provision is made for causing the torpedo to travel at a certain depth below the surface of the water. This is done by means of a beautiful piece of automatic and delicate machinery acting upon small vanes or rudders. This is so set that after it has made its preliminary dive the torpedo will rise, and, after a few oscillations, settle down upon the fixed horizontal course for which it is set. The full speed is about 30 knots an hour, though, if it is desired, the engines may be set to carry the torpedo a greater distance at a slower speed. Great as this speed is, it is not sufficient to insure their keeping ahead of the modern torpedo destroyers, and for this reason the bow launching tubes are no longer built into the fastest boats. In the illustration we are supposed to be standing on a higher deck than that from which the launching takes place, and we are looking forward in the direction in which the ship is steaming. The streaked and milky appearance of the water is caused by the wash from the vessel's bows. Our engraving is from Black and White.

The Sculptor's Profits.

One of the most puzzling problems is to ascertain the ratio between artists' fees and the cost of works at different periods. An attempt of the kind has been made in Berlin, apropos of the memorial of the Emperor William I. For that work the Reichstag voted a sum of 4,000,000 marks, and the expenses, it is believed, will not exceed that sum. Professor Reinhold Begas has received one-fourth of the amount, but as he has not furnished a debit and credit account—nor should he be expected to prepare one for the public gratification—it cannot be ascertained whether he has gained or lost by his great work. But it may well be doubted whether his commission was as profitable as Rauch's when he executed the fine memorial of Frederick the Great, which is so prominent an object in the Unter den Linden. The payment was arranged differently. During the twelve years he was engaged on the work he received 3,000 thalers annually, and he was therefore able to devote himself to his task without anxiety. On the completion of the memorial he received 20,000 thalers; so that in all he obtained 168,000 marks, which was a fourth of the total cost. But the money, amounting to over £8,000, was mainly for his own services, while Professor Begas has had heavy disbursements. Schlüter, the sculptor, was paid 2,000 thalers for his design for the memorial of Frederick I, or the "Reiterbild des Grossen Kurfürsten," which is so

prominent an object on the Lange Brücke, near the Schloss, in Berlin. About the same time he was intrusted with the superintendence of the inclosure to the royal palace. He received from 800 to 1,000 thalers yearly, but whether that was for sculpture alone is uncertain. It is calculated that he was rewarded with 11,000 thalers, or 33,000 marks, which would be about one-eighth of the cost of the most

of the post, and the unraveled ends of the rope are bound around his wrists and tied securely, and all knots are sealed with wax. A large nail is driven in the top of the post, to which are fastened cords that are passed out through the cabinet and held by members of the committee in order that they may know if the performer moves the post in any manner during the performance of any test, such as the ringing of bells, etc. Fig. 2 of our engraving shows the performer tied to the post and the committee holding the cords. The curtains of the cabinet are closed and the usual manifestations take place.

Before the performance a hole is bored in the center of the end of the stick or post, in which is placed a chisel-shaped piece of steel sharpened at the lower end and blunt at the upper end, as shown in Fig. 3. The opening in the end of the post is now carefully closed and all signs of such an opening are concealed by the aid of glue, sawdust, and a little dirt rubbed over it.


When the committee are invited to bore a hole in the post, the performer takes care to start the bit, in order that there will be no mistake about getting the hole directly beneath the chisel concealed in the post. When the rope is passed through the hole and knotted it is directly under the sharp edge of the chisel, with a thin layer of wood between. When the nail is

driven in the top of the post it strikes the chisel, forcing it through the thin shell of wood above the rope and through the rope, thus releasing the performer, who can withdraw his hands from the post and do any trick he chooses, and when finished, by merely replacing the ends of the rope in the holes from which he removed them, and holding the hands tight against the post, can allow a most rigid examination of the seals to show that it was not possible for him to have released his hands, and the persons holding the cords that are fastened to the nail testify that they did not feel any movement of the performer or the post.

Some Startling Figures.

The New York Sun in an editorial bunches some significant pension facts, so that the inference drawn is that a great proportion of pensioners are unworthy of government bounty and that the list should be cut down. Figures recently published show that at the present rate of expenditure the annual pension list has been consuming more than nine-tenths of the revenue taken in at all of the custom houses in the United States; or again, if the customs duties are considered as paying the general expenses of the government, the pensions have been using up not less than 96 per cent of the total receipts from internal revenue. Thirty-two years after the end of the civil war, the number of pensioners on account of that war exceeds by about a quarter of a million the number of soldiers actually engaged in service in all of the armies of the government at any time between the firing upon Sumter and the surrender of Lee at Appomattox. The number of pensioners after a third of a century is between 30 and 40 per cent larger than the fighting army at any time during the war. We have already paid in pensions since the war two billion dollars or two-thirds as much as it cost the government to carry on the war.

ACCORDING to some researches of Biernacki, in a German physical journal, alcohol containing water may be deprived of its water by dipping into it amalgamated aluminum. Aluminum may be amalgamated by connecting it to one pole of a battery and repeatedly dipping it into mercury which is connected to the other pole. The spark produced upon withdrawing it yields sufficient heat to bring about the amalgamation.—Elec. World.



PHOTOGRAPH OF A WHITEHEAD TORPEDO TAKEN JUST AFTER ITS DISCHARGE FROM THE BATTLESHIP.

excellent example of German sculpture in the beginning of the eighteenth century.—The Architect.


THE "SPIRITUALISTIC POST TEST."*

BY W. B. CAULK.

The "spiritualistic post test" is among the latest and most successful of mechanical fastenings. A piece of wood four inches square and three feet long is given to the committee, who bore a hole through it near one end, and then pass an ordinary rope through the hole, tying a knot in the rope on each side of the post, pressing the knots against the post so that the rope cannot be drawn through the post. The ends of the rope are now unraveled, and the post secured to the floor of the cabinet.

The performer, standing behind the post, places his wrists against the knots in the rope, one on each side

* Copyrighted, 1897, by Munn & Company.—From "Magic: Stage Illusions and Scientific Diversions, including Trick Photography." Ready September 15. Price \$2.50. Send for illustrated circular.



THE SPIRITUALISTIC POST TEST.

RECENTLY PATENTED INVENTIONS.

Engineering.

COMBUSTION ENGINE.—Augustus G. Pace, New York City. This engine has two cylinders in which pistons operate, and combustion chambers have port communications at the top and bottom with the cylinders, the pressure of exploded gas being exerted on the top of one piston and the bottom of the other. The gas admission valves are operated by the suction of the pistons, and the exhaust valves by a rotary part of the engine. The engine is designed to be of greatly reduced weight as compared with other combustion engines, while developing a corresponding amount of power.

Railway Appliances.

SWITCH OPERATING DEVICE.—George M. Patterson, Providence, R. I. A mechanism is provided by this invention for automatically shifting switch rails from a siding to the main track, the mechanism being under the full control of the engineer or fireman on the locomotive, and being designed to entirely obviate danger of accident by side tracking a train. It comprises switch tongues pivotally connected with a boxing in which is a spring-actuated block engaged by a spring-actuated plunger, an operating shaft being connected with the boxing, and there being devices on the locomotive cowcatcher by which the switch mechanism may be operated by means of a pull rod which extends into the cab.

Bicycles, Etc.

A NOVEL BICYCLE.—John Carlyle Raymond, Brooklyn, N. Y. On each side of the drive wheel shaft, according to this invention, is a pinion, each pinion meshing with a gear wheel on a crank shaft journaled in bearings of the frame, the shaft having two crank arms, one arm connected by a link with a treadle and the other arm connected by a link with a fulcrumed lever on the forward end of which is the saddle. The construction is designed to afford exercise for the rider's whole body, the up and down motion of the rider in his seat, as well as the pressure on the pedals, assisting to propel the bicycle.

TROLLEY BICYCLE.—Robert T. Oney, Charleston, West Va. This is a wheel adapted to carry an electric motor, and having on the front portion of its frame a jointed extensible trolley pole carrying two trolley wheels to contact with two separate conducting wires, whereby the wheel may be run by the electric current on an ordinary dirt road. The bicycle is provided with the usual pedals, so that it may be propelled in the ordinary way, with the trolley pole folded down in front, or both means of propulsion may be simultaneously employed if desired.

Mining, Etc.

SEPARATING PRECIOUS METALS FROM ORE.—Gustaf M. Westman, New York City. A process for separating gold and silver from refractory ores, according to this patent, comprises the bringing the mass of ore to a molten condition, and then subjecting the running molten mass to the action of jets of steam, air, or other fluid, to form mineral wool, thus causing the minutely divided particles of the precious metal to collect on and adhere to the mineral wool. The latter is then subjected to a leaching process, as with free chlorine gas in a solution, to separate the precious metals from the mineral wool.

Mechanical.

POWER CONVERTING MECHANISM.—Benedict J. Ross, Louisville, Ky. To convert reciprocating into rotary motion, this invention provides a device which consists essentially of bars pivoted together in one or more pairs, similarly to the two bars of a toggle joint, the outer ends of the bars being restrained within guides so that they have a reciprocating movement there-through, while short arms extend at right angles from their outer ends, these arms being connected by rods with double cranks on a shaft. The movement of the center pivot of the bars forming a toggle joint causes a reciprocating movement of the connecting rod and a rotary movement of the shaft.

WORK HOLDER.—Olof R. Johnson, Escanaba, Mich. This is a device in the nature of a bench clamp, more especially designed for the use of carpenters and other mechanics, to hold work in place, and to be itself conveniently placed in position on a bench or board or other support to form a temporary bench to facilitate doing small jobs in houses. It consists principally of a bit plate on which a dog is fitted to slide, a disk turning in an opening in the dog and formed with a spiral groove engaged by a lug or pin on the bit plate. A device is provided for securely fastening the bit plate in position on the bench or board, and auxiliary dogs for holding boards upon edge and holding work in an inclined position.

Miscellaneous.

COMPUTING SCALE.—William R. Dunn, Alton, Ind. A computing or price indicating scale is provided by this invention, a movable weight being adapted to traverse two beams, one graduated to indicate pounds and ounces and the other the price in cents of the substance being weighed. The price-indicating beam is a tubular rotative body, and has on its periphery a longitudinal series of graduations, with an index character at the end of each series, showing the price per pound in the weighing of which each particular series of graduations is to be used, such graduations running, as described, from three to thirty-five cents per pound, or to be varied as desired.

ADDING MACHINE.—William J. Ensworth, Erie, Pa. A machine which may be used for adding columns of figures, or as a cash register in mercantile concerns, is provided by this invention, the operation of the machine being indicated to the operator and others present. The operation is effected by turning arms on registering disks whose peripheries have each a hundred notches, one form of the machine being adapted to add

and register up to ninety-nine dollars and ninety-nine cents and other forms up to thousands and millions.

DRY OIL GAS BURNER.—Charles H. West, Kearney, Neb. For burning oil gases in a dry state, instead of burning the oil in the form of a mist or spray, this burner is made with an overhanging vaporizing pipe and a subadjacent burner pipe, while an adjustable deflector or flame spreader with broad, flat base connects the top and bottom and receives the vaporizing pipe, there being a set screw for adjustably fixing the position of the deflector on the vaporizing pipe. An oil cut-off valve may be adjusted to regulate the amount of heat and flame.

SASH LOCK.—Charles T. Redfield, Glen Haven, N. Y. This lock brings the meeting rails of the sashes together in a manner somewhat similar to the action of a parallel ruler, drawing the rails together and alongside of each other and at the same time forcing them at their opposite ends against the opposite sides of the window frame. The device comprises a slotted link sliding and swinging on a securing stud, and an abutment stud over which the link may readily be applied and removed.

NOTE.—Copies of any of the above patents will be furnished by Munn & Co. for 10 cents each. Please send name of the patentee, title of invention, and date of this paper.

SCIENTIFIC AMERICAN
BUILDING EDITION

SEPTEMBER, 1897.—(No. 143.)

TABLE OF CONTENTS.

- No. 1. Plate in colors, also another perspective elevation and floor plans of a residence at Bensonhurst, L. I., recently erected for Mr. Walter Jones. A design treated in an attractive style of architecture, with Colonial feeling and classic detail. Architect and builder, Mr. Walter Jones.
- No. 2. A Colonial residence at Springfield, Mass., recently completed for Mr. N. N. Fowler, at a cost of \$18,000 complete. Two perspective elevations and floor plans. Mr. Guy Kirkham, architect, Springfield, Mass.
- No. 3. Residence at Scranton, Pa., recently erected for Mr. Thomas R. Brooks. A unique design. Two perspective elevations and floor plans. Mr. John A. Duckworth, architect, Scranton, Pa.
- No. 4. Elm Park Methodist Episcopal church and parsonage at Scranton, Pa. Two perspective elevations and floor plans, also two perspective elevations of the parsonage, with floor plans. Architects, Messrs. George W. Kramer & Co., New York City.
- No. 5. English dwelling at Overbrook, Pa., recently erected for Mr. Smucker. An attractive design treated in the English style, half timber and stone. Perspective elevation and floor plans, also interior view. Architect, Mr. William L. Price, Philadelphia, Pa.
- No. 6. Cottage at Binghamton, N. Y., recently erected for Mr. G. N. North, at a cost of \$3,200. Two perspective elevations and floor plans. A design with many excellent features, good elevations and well arranged plans. Mr. Alfred Bartoo, architect, Binghamton, N. Y.
- No. 7. Modern cottage at Nyack, N. Y., recently erected for the Rev. Edward Mitchell, at a cost of \$2,500 complete. Two perspective elevations and floor plans. A unique design for small cottage. Mr. George F. Morse, architect, Nyack, N. Y.
- No. 8. Modern suburban villa at Chestnut Hill, Mass., erected for Messrs. Merriam, Isenbeck & Alvord. A design well treated in the modern American style with Colonial detail. Two perspective elevations and floor plans. Architect, Mr. J. H. Morse, Boston, Mass.
- No. 9. A residence at Binghamton, N. Y., recently erected for Miss Q. M. French. Perspective elevation and floor plans. A very attractive design with excellent elevations.
- No. 10. An actress' home at Chevy Chase, Md., illustrating the residence of Miss Annie Lewis. Two perspective elevations and floor plans. Mr. Louis D. Meline, architect, Chevy Chase, Md.
- No. 11. Half page design of the New Rathapotheke in Bremen.
- No. 12. Pulpit of the Cathedral of Sainte Gudule, Brussels.
- No. 13. Miscellaneous Contents: New York as a furniture market.—Advantages of fresh air in apartments.—Exterior plaster for dwellings.—Rules for making good mortar.—Premature occupation of new homes; a test for relative humidity of habitable apartments.—Ventilation of apartments.—Does your faucet leak?—A new recording thermometer, illustrated.—Beautiful work in wood finishing.—Slate roofs.—Deco-re-o, illustrated.—Berkfeld filter, illustrated.

The Scientific American Building Edition is issued monthly. \$2.50 a year. Single copies, 25 cents. Thirty-two large quarto pages, forming a large and splendid MAGAZINE OF ARCHITECTURE, richly adorned with elegant plates and fine engravings, illustrating the most interesting examples of Modern Architectural Construction and allied subjects. All who contemplate building, or improving homes or structures of any kind, have in this handsome work an almost endless series of the latest and best examples from which to make selections, thus saving time and money.

The Fullness, Richness, Cheapness and Convenience of this work have won for it the LARGEST CIRCULATION of any Architectural Publication in the world. Sold by all newsdealers. MUNN & CO., PUBLISHERS, 361 Broadway, New York.

Business and Personal.

The charge for insertion under this head is One Dollar a line for each insertion; about eight words to a line. Advertisements must be received at publication office as early as Thursday morning to appear in the following week's issue.

Marine Iron Works. Chicago. Catalogue free.

"U. S." Metal Polish. Indianapolis. Samples free.

Yankee Notions. Waterbury Button Co., Waterbury, Ct. Handle & Spoke Mch. Ober Lathe Co., Chagrin Falls, O.

Improved Bicycle Machinery of every description. The Garvin Machine Co., Spring and Varick Sts., N. Y.

Concrete Houses—cheaper than brick, superior to stone. "Ransome," 757 Monadnock Block, Chicago.

For Business Opportunities in Virginia, address Paul Scherer, Industrial Agt. N. and W. Ry., Roanoke, Va.

A limited number of high grade motor wagons for sale. Address Motor Wagon, P. O. Box 773, New York.

The Norwich Line—New York to Worcester, Lowell, Gardner, Winchendon and Keene, N. H. From Pier 40, North River, 5:30 P. M., week days only.

The celebrated "Hornsby-Akroyd" Patent Safety Oil Engine is built by the De La Vergne Refrigerating Machine Company. Foot of East 138th Street, New York.

The best book for electricians and beginners in electricity is "Experimental Science," by Geo. M. Hopkins. By mail, \$4. Munn & Co., publishers, 361 Broadway, N. Y.

A preparation for preventing rust on bright surfaces of machinery and tools has just been put upon the market by Messrs. Golding & Company, of Boston, Mass., after having fully tested its qualities by several years' use on their own manufactures. It is made in two grades, heavy for machinery and light for tools, is quickly applied with a brush or cloth, can be readily removed by vigorous rubbing with cloth or waste, and benzine or turpentine will dissolve it. It fills the pores of the metal, leaving a thin film that is impervious to the salty atmosphere of the sea, snow, acid fumes, or any condition of dampness in factory or transportation. Made and sold by Golding & Company, Boston, New York, Philadelphia and Chicago.

Send for new and complete catalogue of Scientific and other Books for sale by Munn & Co., 361 Broadway, New York. Free on application.

Notes & Queries

HINTS TO CORRESPONDENTS.

Names and Address must accompany all letters or no attention will be paid thereto. This is for our information and not for publication.

References to former articles or answers should give date of paper and page or number of question.

Inquiries not answered in reasonable time should be repeated; correspondents will bear in mind that some answers require not a little research, and though we endeavor to reply to all either by letter or in this department, each must take his turn.

Buyers wishing to purchase any article not advertised in our columns will be furnished with addresses of houses manufacturing or carrying the same.

Special Written Information on matters of personal rather than general interest cannot be expected without remuneration.

Scientific American Supplements referred to may be had at the office. Price 10 cents each.

Books referred to promptly supplied on receipt of price.

Minerals sent for examination should be distinctly marked or labeled.

(7197) W. T. P. asks: 1. Could some one describe the most effective electro-magnet to give a lift of 5 inches at a pressure from 50 to 75 pounds? And state how much electricity it would take to work the same in volts and amperes. A. The electro-magnet best suited to your purpose, probably, is the coil and plunger. The coil would be 15 inches long and the winding would have 17,000 turns of No. 18 wire. The iron core should be a bar about 2½ inches in diameter and 20 inches long, in order to get the very long pull you specify. The type of magnet is described in S. P. Thompson's "Electro-magnet," page 54, and shown in Fig. 30, page 55. 2. And state which is the most productive of magnetism, volts or amperes? I have a generator that gives 50 volts and 3½ amperes. Shall I be able to produce enough magnetism to give me the desired lift? A. The current for the above winding is 3½ amperes. The ampere turns give the lifting power. One ampere going once around the core constitutes an ampere turn; 60,000 ampere turns are provided for in the above winding, and there is a surplus of iron in the core as an allowance for safety.

(7198) W. E. B. asks: Will you please give the process of laying water-tight cement floor over boards? A. A board floor for a water-tight cement cover should be made of very narrow thick stuff, say 2 inches wide and 1½ inches thick, on beams close enough to prevent springing. The upper corner of the flooring strips should be slightly beveled to allow of the cement pressing in between the boards to prevent cracking; bottom edge of flooring should be laid tight. Portland cement should be used and laid thick enough to prevent breaking up by the special use of the floor.

(7199) E. N. M. asks: Will you please inform me through the Notes and Queries columns of your paper how to make a selenium cell, such as is used in electrical experiments? You will find valuable articles on selenium cells in SUPPLEMENT, Nos. 246, 264, 270, 271, 281, 283, 676, and 749, which we can supply at 10 cents each.

(7200) J. E. S. asks: Can you give me any information regarding flash boilers? A. The flash boiler has been the subject of engineering experiment during the past thirty years with no practical result beyond a few horse power. On the larger scale the unequal heating of the steam-making surfaces has produced unequal expansion to such an extent as to ruin every boiler tried in a very short time. The Reid boiler went through several forms, the principal of which was two cylindrical shells, concentric, vertical, with a space of ¼ of an inch between them, with jets distributing the water upon the hot surfaces as evenly as possible with the surplus, if any, falling to the bottom. The fire box was beneath the boiler, with the heated gases rising in contact with both inside and outside of the shell. The Mitchell boiler was a revolving cylinder over the

furnace so that its entire surface became an intense heating surface. The water was fed through a stuffing box on one of the journals, with a central perforated pipe that jetted the feed water in all directions, the steam being taken from the opposite journal with a stuffing box connection. The only style of flash boiler that has done any real service is the coiled pipe form with the water injected at the bottom, which, by its foaming with the sudden heat, rises through the coil and is all converted into steam. The coiled pipe boilers have been of many forms, the most durable of which are made in a single length of extra strong iron pipe. The most successful of the pipe boilers are of the kind made by Serpollet, in Paris, France, and used on steam carriages in the recent road motor trials. The Serpollet is illustrated and described in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 664 and 732. Ten cents each, mailed.

(7201) J. L. writes: Will you kindly send me a receipt for tempering four ribbed reamer so it will harden and not curve? I have tried oil and salt water and they curve. I have given you the drawing so as to make it as clear as possible. A. The sketch of our correspondent represents an ordinary four ribbed reamer—12 inches long, taper, and of small size. The hardening of long slender tools is the most difficult operation in the machinist's hands. We can only advise the necessary precautions used by those who succeed. The steel should be annealed a second time before the last cut is made, by heating slowly in a low fire buried in an iron box or tub of clear ashes or fine sand; then finished. The heating for hardening should be done in the same way as before, with a little pulverized charcoal mixed with the ashes or sand. When the box and reamer has been heated through, to a full cherry red, the reamer should be carefully drawn out endwise so as to prevent the possibility of bending while hot; and immediately dipped vertically in oil, not too quickly. Any variation from the vertical is liable to warp the tool by cooling one side faster than the other. In drawing temper care should also be taken to heat evenly on all sides alike to the straw color, brown, or light blue, for whatever use the tool is for. The long delicate reamers of the tool trade are tried with an emery wheel and guiding machine.

(7202) L. L. S. asks how to make dry cells for faradic and galvanic batteries, e. g., as the chloride of silver dry cell batteries. A. To make the chloride of silver cell, provide a glass tube about 1 inch in diameter and 3 inches high. This is closed at the top by a cork. Through the cork passes a rod of chemically pure zinc, which may extend to within ¾ inch of the bottom of the tube. This is the positive plate. The negative plate consists of chloride of silver cast around a silver wire, and wrapped in fine parchment paper. To prepare the negative plate, melt the chloride of silver in a porcelain crucible and cast it in a hard carbon mould upon a silver wire, long enough to extend through the stopper and attach to the zinc of the next cell in series. The charging solution is made by dissolving 1 ounce of pure ammoniac chloride (sal ammoniac) in 1 quart of water. The tight fitting stopper retains the liquid in the cell. If the cell is not overworked, no gas is formed by it; so that there is usually no need of a vent. The cell is thus a watertight rather than a dry cell. Dry cells are made by mixing plaster of Paris, gelatine, or similar substances with saturated solution of sal ammoniac in water, so that the liquid will not run out of the mass. In this sense only they are dry. This is packed between and around the zinc and carbon. Much valuable information regarding dry cells and a description of many types will be found in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1001, 10 cents.

(7203) J. M. W. asks for formulas for aromatic vinegar: A. 1. Henry's.—Dried leaves of rosemary; rue, wormwood, sage, mint and lavender flowers, each ¼ oz.; bruised nutmeg, cloves, angelica root and camphor, each ¼ oz.; alcohol (rectified), 4 oz.; concentrated acetic acid, 16 oz.; macerate the materials for a day in the spirit; then add the acid and digest for a week longer at a temperature of 14° or 15° C. Finally, press out the now aromatized acid and filter it. 2. Concentrated acetic acid, 8 oz.; otto of English lavender, 2 drachms; otto of English rosemary, 1 drachm; otto of cloves, 1 drachm; otto camphor, 1 oz. First dissolve the bruised camphor in the acetic acid, then add the perfumery, after remaining together for a few days, with occasional agitation, filter. All vinegars are used by pouring 3 or 4 drachms into an ornamental smelling bottle, previously filled with crystals of sulphate of potash.

NEW BOOKS, ETC.

A PRACTICAL MANUAL OF LINSEED OIL MANUFACTURE AND TREATMENT. Varnish manufacture, superior, medium and cheap grades. By John Bannon. New York and Chicago: Published by the National Provisioner Publishing Company. 1897. Pp. 217. Price \$10.

Linseed oil is a very essential constituent of a good paint or varnish, and it is strange that there should be so little literature on the subject. The present work is by a man who is thoroughly acquainted with the manufacture of linseed oil and linseed oil varnishes, and possesses great value on this ground. The subject is treated in order and the latest methods of manufacturing oil are described. Toward the end of the book the manufacture of varnishes is taken up and a number of tested formulas are given. This book is an addition to technological literature of the utmost importance, and all who are in any way interested directly or indirectly in the manufacture of linseed oil should possess a copy.

Sargent's "Book of Designs" is the title of a very beautifully got up and handsomely illustrated monograph, in quarto form, issued by Sargent & Company, of New York, makers of artistic hardware and fine locks with the view of making the public better acquainted with the elegant designs and fine finish of the goods produced by the house. The company is one of the oldest and largest in this line of business, and the great variety and beauty of their several finishes in antique copper, old brass, oxidized silver, etc., of such articles as escutcheons, door plates and knobs, locks, butts and hinges, and other household trimmings, are well brought out in the fine half tones furnished in this "Book of Designs." It is sent free to applicants.

Advertisements.

ORDINARY RATES.

Inside Page, each insertion, - 75 cents a line
Back Page, each insertion, - - \$1.00 a line

For some classes of Advertisements, Special and Higher rates are required.

The above are charges per agate line—about eight words per line. This notice shows the width of the line, and is set in agate type. Engravings may be advertised at the same rate per agate line, by measurement, as the letter press. Advertisements must be received at Publication Office as early as Thursday morning to appear in the following week's issue.

Star Lathes Foot power Screw...cutting Automatic Cross feed
9 and 11-inch Swing.
New and Original Features
Send for Catalogue B.
Seneca Falls Mfg. Company,
695 Water St., Seneca Falls, N.Y.

SCIENTIFIC AMERICAN SUPPLEMENT.—Any desired back number of the SCIENTIFIC AMERICAN SUPPLEMENT can be had at this office for 10 cents. Also to be had of newsdealers in all parts of the country.

POWER & FOOT LATHES. SHAPERS, PLANERS, DRILLS, MACHINE SHOP OUTFITS, TOOLS AND SUPPLIES. CATALOGUE FREE. SEBASTIAN LATHES CO. 120 CULVERT ST. CINCINNATI, O.

HAVE THE LATEST IMPROVEMENTS. No machine shop can be thoroughly up-to-date unless it has the most modern perfected tools. For instance, the

ASHLEY PATENT NIPPLE HOLDERS hold nipples for cutting either right or left hand threads. They hold the sleeve from turning and take the strain off both the sleeve and shank thread. Made of best quality cast steel, carefully fitted. Long or short nipples cut with equal facility. The Ashley Holders are of light weight and compact form.
WALWORTH MFG. CO., 20 Oliver St., Boston, Mass.

SAVE 1/2 YOUR FUEL
By using our (stove pipe) **RADIATOR.** With its 120 Cross Tubes, ONE stove or furnace does the work of TWO. Drop postal for proofs from prominent men.
TO INTRODUCE OUR RADIATOR, the first order from each neighborhood filled at **WHOLESALE** price, and secured an agency. Write at once.
ROCHESTER RADIATOR COMPANY,
82 FURNESS ST., ROCHESTER, N. Y.

NEW HACK SAW FRAMES.
Saw may be instantly attached or removed or set at any angle. Finely finished and made of selected Cocobola handles. Catalogue of Fine Tools Free.
L. S. STARRETT CO., MASS.
Box 13, Athol, U. S. A.

DEFIANCE MACHINE WORKS
DEFIANCE, OHIO, U.S.A.
BUILDERS OF
HUB, SPOKE, WHEEL BENDING, WAGON CARRIAGE AND HOOP MACHINERY.
SEND FOR CATALOGUE

ROCK DRILLS AIR COMPRESSORS
SIMPLEST, MOST EFFICIENT and DURABLE.
RAND DRILL CO.
Send for Catalogue. 100 Broadway, New York.

BARNES' UPRIGHT DRILLS
Complete line, ranging from Light Friction Disk Drill to 42" Back Geared Self-Feed. Send for New Catalogue.
W. F. & JOHN BARNES CO.
1999 Ruby Street, ROCKFORD, ILL.

THE COBURN PATENT TROLLEY TRACK HOUSE DOOR HANGERS
The first made with adjustable track. The track can be put up in 30 minutes.
Send for Book.
The Coburn Trolley Track Mfg. Co., Holyoke, Mass.

PRATT'S CONE BELT SHIFTER
Simple in construction, easily applied. Saves time to manufacturers, TROUBLE to operator, and WEAR to belts. In ordering give width of belt.
For Belts 1 to 2 1/2 inches wide, \$3.50
2 1/2 to 4 4.50
Send for catalogue of machinists' tools
CHANDLER & FARQUHAR,
38 Federal St., BOSTON, MASS.

PORTABLE SINGLE RAIL SURFACE Railway. Details of construction and description of rolling stock of a new system of portable railway which may be laid upon ground that has received no special preparation for its reception. With 19 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1014. Price 10 cents. To be had at this office and from all newsdealers.

CARBORUNDUM
HARDEST ABRASIVE KNOWN. EMERY AND DIAMOND POWDER SUBSTITUTE. IN FLOUR, POWDER, CRYSTAL, WHEEL, SLAB & HONE FORM.
CARBORUNDUM CO. NIAGARA FALLS, N.Y., U.S.A.

Woodworkers' Tools.

Your money back if you want it. Suppose you should send us 25 cents for our new Catalogue of

Woodworkers' Tools
400 pages, 1800 illustrations, and after receiving it were not satisfied. Such a supposition is of course absurd, but if it were the case, we'd return the quarter and tell you to keep the book.

The Chas. A. Strelinger Co.
Address Box 134, DETROIT, MICH.

PHYSICAL AND SCHOOL APPARATUS
TOEPLER HOLTZ SELF CHARGING MACHINE
For School, College or X Ray work.
Circular free.
E. S. RITCHIE & SONS,
Brookline, Mass.

STEAM STAMP MILL
A mill for crushing ores. Equal in efficiency to a five stamp battery, and at a fraction of the expense.
A boon alike to the prospector and mining capitalist. Send for catalogue.
GATES IRON WORKS, Dept. C,
650 Elston Ave., Chicago, U. S. A.

PIERCE 2 ACTUAL H. P.
PRICE, Complete, \$135.00.
Made for Gas or Gasoline.
MARINE ENGINES TO 4 H. P.
16, 18 and 21 foot Launch Outfits complete. All sizes Stationary to 25 h. p.
Send for Circular of size wanted.
PIERCE ENGINE CO.
17 N. 17th St., Racine, Wis.

MANUFACTURE OF BICYCLES.—A very comprehensive article giving the details of construction of every part of these vehicles. With 15 engravings. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 908. Price 10 cents. To be had at this office and from all newsdealers.

POWER? POWER? POWER!
Fifty per cent. increase at no additional expense.
VICTOR VAPOR ENGINE.
LOCAL AGENTS WANTED.
Steam and Vapor Launches Row and Sail Boats.
Send for catalogue. Specify one wanted.
THOS. KANE & CO.
64-66 Wabash av., Chicago.

DYNAMOS
For Lighting and Plating
20 light - - - \$40.00
50 light - - - 75.00
100 light - - - 125.00
MOTORS
1/4 h. p., \$15; 1/2 h. p., \$25; 1 h. p., \$40; 2 h. p., \$60.
Storage batteries and propeller wheels for boats.
EVANS ELECTRIC CO.
61 and 63 N. Ashland Ave., Chicago, Ill.

GAS and GASOLINE ENGINES.
Using Natural Gas, Coal Gas, Propane Gas, and Gasoline direct from the tank.
1 to 40 H. P., actual.
The Springfield Gas Engine Co.
21 W. Washington St. Springfield, O.

ACETYLENE APPARATUS.—ACETYLENE number of the SCIENTIFIC AMERICAN SUPPLEMENT, describing, with full illustrations, the most recent, simple, or home made and commercial apparatus for generating acetylene on the large and small scale. The gas is made for and used by the microscopist and student; its use in the magic lantern. The new French table lamp making its own acetylene. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1037. Price 10 cents. To be had at this office.

OLDS ENGINE
The Engine that has No Gears or Levers.
Simplest Carburetor. Wonderful economy. Had 12 years of success.
Know the requirements of a Gas Engine.
P. F. Olds & Son Engine Works, Box 418, Lansing, Mich.

MONITOR AND MOGUL
MARINE GAS ENGINES.
LAUNCHES.
NO INSPECTION, BOILER, FIRE, HEAT, SMOKE OR ODOR.
MONITOR
VAPOR ENGINE AND POWER COMPANY
GRAND RAPIDS, MICH. SEND FOR CATALOGUE.

GREENFIELD Steam Engine Works.
Established 1874.
Manufacturers of Greenfield Stationary, Portable and Yacht
ENGINES AND BOILERS.
Also Horizontal, Automatic and Variable Cut-off Engines. Sizes from 3 to 75 Horse Power.
Also Vertical and Horizontal and Marine Boilers, Steam Pumps and Adams' Grate Bars.
W. G. & G. GREENFIELD,
East Newark, N. J.

TO INVENTORS.

An experience of nearly fifty years, and the preparation of more than one hundred thousand applications for patents at home and abroad, enable us to understand the laws and practice on both continents, and to possess unequalled facilities for procuring patents everywhere. A synopsis of the patent laws of the United States and all foreign countries may be had on application, and persons contemplating the securing of patents, either at home or abroad, are invited to write to this office for prices, which are low, in accordance with the times and our extensive facilities for conducting the business. Address **MUNN & CO.,** office SCIENTIFIC AMERICAN, 361 Broadway, New York.

INDEX OF INVENTIONS

For which Letters Patent of the United States were Granted

AUGUST 24, 1897,

AND EACH BEARING THAT DATE.

[See note at end of list about copies of these patents.]

Advertising card, C. F. Engstrom.....	588,636
Advertising vehicle, C. S. Stafford.....	588,783
Air brake, W. K. Omick.....	588,913
Air ship, T. M. Crepan.....	588,556
Alarm, See Burglar alarm.....	
Anchor, D. Hoyt.....	588,767
Armature for induction motors, A. L. Cushman.....	588,622
Axle sleeve, vehicle, Westmoreland & Babington.....	588,759
Bag fastener, T. J. P. Maus.....	588,717
Bag fastener, N. F. Wightman.....	588,848
Bag tie, A. Davison.....	588,855
Bandage cutting machine, J. R. Volz.....	588,844
Barrel head, J. F. Adams.....	588,763
Battery, See Electric battery.....	
Bearing, roller, J. R. Richardson.....	588,837
Bearings, oil retainer and distributor for hollow rolls of roller, Tellefsen & Lockwood.....	588,667
Bed attachment, D. B. Ware.....	588,622
Bell, bicycle, Foley & Birch.....	588,900
Bellevue, W. E. Gar.....	588,820
Belt, applying device, Savage & Wade.....	588,838
Bicycle, H. F. Blank.....	588,628
Bicycle, J. H. Eickershoff.....	588,628
Bicycle alarm, R. Hartmann et al.....	588,573
Bicycle attachment, W. P. Brodbeck.....	588,551
Bicycle crank hangers, mechanism for making, N. E. Parish.....	588,804
Bicycle foot rest, W. W. Nisbet.....	588,873
Bicycle mud guard, N. Hoyt.....	588,922
Bicycle or other vehicle, J. H. Eickershoff.....	588,637
Bicycle shoulder brace, A. Roberts.....	588,881
Bicycle steering lock, safety, R. W. Smith.....	588,895
Bicycle two-speed driving gear, Reilly & Hagen.....	588,657
Blower and exhaustor, W. Schuster.....	588,735
Boiler, See Water tube boiler.....	
Boiler water gage, steam, Robinson & Donald.....	588,605
Boots or shoes, appliance for easing, S. Learoyd.....	588,703
Bottle, non-collapsible, E. Eiley.....	588,603
Bottle stopper, D. T. Phillips.....	588,775
Bottles, etc., closing piece for, G. W. Steffens.....	588,734
Box, See Fare box.....	
Box, H. S. Munson.....	588,871
Box covering machine, Smith & Bullock.....	588,887
Brake, See Air brake. Car brake. Track brake. Wagon brake.....	
Brick drier, H. H. Walsh.....	588,621
Bucket, berry, W. W. Roland.....	588,930
Buckle, bridge blinder, J. Mealey.....	588,590
Bulkhead doors, means for automatically operating, Dorr & Schuler.....	588,793
Burglar alarm, electric, H. M. Dumas.....	588,635
Burner, See Hydrocarbon burner. Oil burner.....	
Butter cutting machine, C. T. Colby.....	588,814
Calendar holder, H. Brown.....	588,631
Camera, roll holding, P. K. Stern.....	588,611
Can, A. W. Livingston.....	588,800
Can, C. Hoyt.....	588,911
Cane and umbrella, combined, J. H. Nolan.....	588,595
Car bolster, J. W. Cloud.....	588,555
Car brake and fender, emergency, A. Grieves.....	588,824
Car coupling, Graham & McGee.....	588,821
Car draught apparatus, railway, W. Thornburgh.....	588,722
Car fender, M. Bettmer.....	588,816
Car fender, J. K. Young.....	588,847
Car, railway, J. L. Finley.....	588,849
Car strap and handhold, F. E. Benton.....	588,563
Car tank, P. Brown.....	588,893
Carbide, or manufacturing, J. W. Wadsworth.....	588,742
Carpet beating machine, J. H. Ibel.....	588,866
Carriage wheel, J. Lindsay.....	588,678
Cartridge, M. P. Boss.....	588,632
Cartridges, automatic machine for wadding and cupping, W. M. Dunn.....	588,764
Carving machine, A. D. Seaman.....	588,601
Case, See Show case.....	
Cash register, C. J. Ryberg.....	588,733
Chain coupling, drive, E. F. Morse.....	588,704
Chair, See Nursery chair.....	
Chair, L. Johnson.....	588,829
Cigar bunching machine, H. Jerstern.....	588,912
Cigarette machine, G. H. Hilgartner.....	588,909
Cinder shield, J. F. Adams.....	588,739
Clasp, See Garment clasp.....	
Clasp, C. R. Bradley et al.....	588,674
Clasp, W. Evans.....	588,560
Clay working machinery, feed regulator for, H. C. Ingraham.....	588,715
Cleaner, See Flue cleaner. Fruit cleaner.....	
Clevis, plow, O. Lade.....	588,653
Clock, alarm, A. Bannatyne.....	588,809
Clock, alarm, J. W. Brewster.....	588,829
Cock with driving parts entirely isolated from liquids, E. Draullette.....	588,765
Collating machine, T. C. Dexter.....	588,635
Concentrating machine, W. M. Moore.....	588,832
Concentrating machine, S. W. Vale.....	588,834
Condenser, C. O. Lindroth, L. Bly.....	588,598
Conveyor, pneumatic, A. P. Heslop.....	588,908
Conveyors, adjusting mechanism for feed chutes for, K. Dodge.....	588,801
Conveyors, automatic feed spout for, J. M. Dodge.....	588,899
Conveyors, for registering machine, L. J. Burdick.....	588,727
Counting and signaling apparatus, B. E. Waters.....	588,670
Coupling, See Car coupling. Chain coupling.....	
Crushing machine, T. L. & T. J. Sturtevant.....	588,618
Cutter, See Vegetable cutter.....	
Cyclometer, L. J. Burdick.....	588,726
Cylindrical or registering machine, L. J. Burdick.....	588,727
Digger, See Post hole digger. Potato digger.....	
Door holder, J. F. Sullivan.....	588,619
Door structure, storm, T. Van Kannel.....	588,888
Drapery pin or hook, J. Smith.....	588,886
Drawer, friction, L. C. Friesen.....	588,665
Drawers support, W. H. Kephart.....	588,750
Drier, See Brick drier.....	
Drill, F. Raymond.....	588,929
Drill frame, P. Broadbooks.....	588,712
Drinking fountain, M. Meeres.....	588,722
Egg beater, C. F. Smith.....	588,663
Egg tester, H. C. Timms.....	588,736
Electric battery, W. Mills.....	588,501
Electric circuit, N. Marshall.....	588,686
Electric lighting system, F. W. Lord.....	588,683
Electric machine, dynamo, L. C. Rice.....	588,602
Electric wick lighting device, H. Van Hoevenbergh.....	588,669
Electrodes of electric accumulators, active material for, S. Hammacher.....	588,905
Elevator, See Water elevator.....	
Elevator safety lock, G. W. MacKenzie.....	588,588
Elevator slipper, M. McNamara.....	588,651
Engine, See Gas engine. Traction engine.....	
Engine, C. Lindroth, L. Bly.....	588,629
Engine igniter, gas, White & Middleton.....	588,917
Engraving, W. S. Eaton.....	588,558
Envelope, R. Johnston.....	588,679
Envelope and packing case, mailing, J. F. Wilhelm.....	588,892
Eyeglasses, A. M. Wad.....	588,723
Fan, fly, G. E. Painter.....	588,754
Fare box, J. Quinn.....	588,778
Fence, wire, C. C. Carter.....	588,896
Fence, wire, J. C. Perry.....	588,774
Fifth wheel, J. Koenig, Jr.....	588,644
Fire escape, portable, W. E. Wadsworth.....	588,889
Fire escape, portable automatic, J. H. Bryan.....	588,894
Fire kindler, L. H. Clark.....	588,633
Fish bait, artificial, C. R. Harris.....	588,729
Flower holder, J. K. Saarlo.....	588,659
Flue cleaner, rotary, L. J. Jones.....	588,830
Fountain, See Drinking fountain.....	

(Continued on page 158)

DRAWING AND DESIGNING

Mechanical & Architectural Drawing; Marine, Stationary or Locomotive Engineering; Mining; Prospecting; Metal Pattern Cutting; Plumbing; Railroad, 31 COURSES & Bridge Engineering; Surveying and Mapping; Book-keeping, Shorthand; English Branches; Architecture; Electricity; Machine Design. All who study **GUARANTEED SUCCESS.** **TAUGHT BY MAIL.** **Free Moderate, Advance or Installments.** Circular Free: State subject you wish to study. International Correspondence Schools, Box 942, Scranton, Pa.

MICHIGAN COLLEGE OF MINES

A State technical school. Practical work. Special facilities for men of age and experience. Elective system. 45 weeks a year. Non-resident tuition \$150 a year. For Catalogue, address **DR. M. E. WADSWORTH, President, Houghton, Mich.**

WASHINGTON, D. C., Bliss Building.

Bliss School of Electricity

The only institution teaching practical electrical engineering exclusively. Laboratory equipment excellent. Courses open October 1st. Catalogue on application.

Uncle Sam's Examinations
for civil service appointments will soon be held in every State. More than 6000 appointments will be made annually! The purpose of the National Correspondence Institute is to prepare any one by mail to pass any civil service examination with a high average, thus assuring early appointment. Particulars about all Gov't positions, dates of examinations, etc., free. National Correspondence Institute (Inc.), Dept. C. S. 2d Nat'l Bldg, Washington, D. C.

THE IMPROVED GAS ENGINE.

Two cylinders in one casting. Occupies less space and weighs less for its power than any engine made. Can be used wherever power is required. Either stationary or marine. No fire. No heat. No smoke. No licensed engineer required. Send for catalogue.

SINTZ GAS ENGINE CO.,
Grand Rapids, Mich., U. S. A.

This beats Wind, Steam, or Horse Power. We offer the **WEBSTER 2 1/2 actual horse power GAS ENGINE** for \$150, less 10% discount for cash. Built on interchangeable plan. Built of best material. Made in lots of 100 therefore we can make the price. Boxed for shipment, weight 300 pounds. Made for Gas or Gasoline. Write for Special Catalogue.
WEBSTER M'FG CO.,
1074 West 15th Street, CHICAGO.

The Long-Sought-For Found at Last

AN IMPULSION WITH EVERY TURN OF THE CRANK. The Hicks Compound Cylinder Gas and Gasoline Engine.

The Engine of the future. This engine will run steadily and reliably as the best automatic steam engine, and much better than the ordinary single cylinder. Catalogue free. **Frontier Iron Works, 601 ATWATER ST., DETROIT, MICH.**

ACETYLENE GAS AND CARBIDE OF Calcium.—All about the new illuminant, its qualities, chemistry, pressure of liquefaction, its probable future, experiments performed with it. A most valuable series of articles, giving in complete form the particulars of this subject. Apparatus for making the gas, contained in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 948, 1004, 1007, 1012, 1014, 1015, 1016, 1022, 1035 and 1038. The most recent apparatus of simple and more elaborate type described and illustrated in special acetylene Supplement No. 1057. Price 10 cents each. To be had at this office and from all newsdealers.

ALGO VAPOR LAUNCH

Motor controlled from bow. Valve movement, 12 to 1, 16 to 60 ft. Launches. Twin Screws a specialty. 1, 2, 3, 5, 7, 12, 14 and 20 h. p. No licensed engineer or pilot required. Speed and Safety guaranteed. No dangerous Naphtha or Gasoline used. No disagreeable vibration. Send Ten Cents in Stamps for 1897 Catalogue.
Marine Vapor Engine Co., ft. Jersey Av., Jersey City, N.J.

New Supplement Catalogue!

An entirely New Supplement Catalogue is now ready for distribution; it includes all of the papers up to and including the first half of the year 1897. It is arranged on a clear and easily understood plan, and contains 10,000 papers more than the former one. It will be sent free to any address in the world on application.

A special edition on heavy paper, handsomely bound in cloth, has also been issued. It is supplied at the nominal cost of 25 cents, and thus enables the possessor to preserve this valuable reference catalogue.

MUNN & CO., Publishers,
361 Broadway, New York City.

The Inland Printer
Is the journal par excellence for printers and all lovers of fine art in the printed page. Is a repository of technical and general information on
HOW TO TASTEFULLY PREPARE
printed matter, illustrations, and everything pertaining to these and allied arts. An artistically designed cover, by Leyendecker, new each month, and other choice features throughout. Its price the only cheap thing about it—\$2.00 per year, 20c. per month.
THE INLAND PRINTER CO., 212-214 Monroe St., CHICAGO.

Tools For All Trades

You can't even think of a Tool that isn't mentioned in our 1897 Tool Catalogue. Every Metal Worker, every person interested in Machinery or Machinery Supplies, needs it in his business. It contains 710 pages, 10x14 inches, and is a complete Tool Encyclopedia. Handsomely bound in cloth, express paid on receipt of \$1.00. Money paid for book will be refunded with first order amounting to \$10.00 or over.
MONTGOMERY & CO.
MAKERS AND JOBBERS IN
FINE TOOLS,
105 Fulton Street, New York City.

USE OF HOT AIR IN DRYING.—BY E. M. Cook. A paper in which the author demonstrates the great economy of the use of hot air over that of steam for drying many materials, especially those in lumps, grain, or powder. With 3 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 1022 and 1023. Price 10 cents each. To be had at this office and from all newsdealers.

MEWER AUTOMATIC FEED DRILL.
An indispensable Labor Saver. Will feed, fine or coarse, at any angle, without pressure or loss of power. Warranted.
For particulars, prices, etc.,
MEWER TOOL CO.
16 Elm St., Portland, Me., U. S. A.

A Pleasant Home
is a combination of all that is beautiful and useful. A tistic Hardware selected from "Sargent's Book of Designs" is beautiful and useful as well. If you propose building, a copy of this book will be sent free upon application to Sargent & Co., 37 Chambers St., New York.

LIGHT AND ELECTRIFICATION.—BY Oliver J. Lodge. The fundamental facts of a new branch of physics, the subject of photo-electric action, the influence of illumination upon electrified surfaces. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1016. Price 10 cents. To be had at this office and from all newsdealers.

AMERICAN UNDERWRITER WATER RELIEF VALVE.
For use on Pumps—either Steam, Rotary or Plunger.
AMERICAN CYLINDER RELIEF VALVES.
Send for Catalogue A.
AMERICAN STEAM GAUGE CO.,
34, 36 & 38 Chardon St., Boston, Mass.

DROP FORGINGS
WYMAN & GORDON
WORCESTER, MASS.
28 BRADLEY STREET.

THE TIN PLATE INDUSTRY IN THE UNITED STATES.—An interesting paper, showing the extraordinary development of the tin plate industry in this country, and the serious competition into which it is now entering with the British industry. With 18 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 1019, 1020, 1021, 1022 and 1023. Price 10 cents each. To be had at this office and from all newsdealers.

Pipe Threading Machines
of Highest Merit.
COMBINATION BENCH and PIPE VISES.
Catalogue containing interesting information free.
Bignall & Keeler Mfg. Co.,
Box S., Edwardsville, Ill.

If you want the best Lathe and Drill
GNUGKS
BUY WESTCOTT'S Strongest Grip, Great Capacity and Durability, Cheap and Accurate.
Westcott Chuck Co., Oneida, N. Y., U. S. A.
Ask for catalogue in English, French, Spanish or German.
FIRST PRIZE AT COLUMBIAN EXPOSITION, 1893.

I PRINT MY OWN
Cards, circulars, with \$5 Press and save money.
Make money printing for others. Our 413 Press prints a newspaper. Type setting easy, printed rules. Send stamp for catalogue, press and supplies, to the factory.
KELSEY & CO.
Meriden, Conn.

MODERN PHOTOGRAPHURE METHODS.—By Horace Wilmer. An interesting description of the process of making photographure plates for illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1007. Price 10 cents. To be had at this office and from all newsdealers.

NICKEL AND Electro-Plating Apparatus and Material.
Hanson & VanWinkle
Co.,
Newark, N. J.
136 Liberty St., N. Y.
35 & 37 S. Canal St., Chicago.

Fruit cleaner, A. Chambers.....	588,854
Furnace, See Heating Furnace.....	
Fuse, shell, Hale & Reavill.....	588,630
Gage, See Boiler water gage.....	588,861
Game apparatus, parlor, W. L. Bass.....	588,811
Garden tool, combination, E. O. Simmons.....	588,757
Garment clasp, J. Stern.....	588,841
Gas engine, C. Quast.....	588,876
Gas generating apparatus, acetylene, D. C. Mor- ency.....	588,593
Gas meter, J. H. Buckingham.....	588,632
Gate, B. P. Rice.....	588,732
Gear teeth, machine for generating, H. C. War- ren.....	588,738
Gearing, differential, De Dion et al.....	588,856
Gearing, sprocket and chain, G. E. Humphreys.....	588,577
Gin feed for roller compresses, C. L. Bessonetie.....	588,812
Glass blower's mould, M. J. Owens.....	588,926
Glass, making plate, C. C. Hartung.....	588,574
Glass press, R. G. Hemingray.....	588,736
Gold and silver ores, apparatus for treating, B. Becker.....	588,740
Governor and speed indicator, non-centrifugal, J. F. Raders.....	588,655
Graders, gravel colter attachment for road, W. L. Caverley.....	588,554
Grain feeder and conveyor, B. S. Constant.....	588,815
Grinding machine, A. Espinasse.....	588,637
Grinding machine, ball, D. Roche.....	588,915
Grooming and clipping machines, balance arm for power, C. W. Potter.....	588,706
Hame, sheet metal, C. F. Mock (reissue).....	11,627
Handle for tools and bicycle handle bars, K. H. Granger.....	588,794
Harmonica, mouth, J. Hohner.....	588,920
Harvester, L. Hammer.....	588,862
Harvester, E. A. Peck.....	588,599
Harvester, potato, H. R. Kuersten.....	588,582
Hat trimming fastener, G. Barnum.....	588,937
Headlight, locomotive, G. B. Rait.....	588,878
Heating apparatus, B. Price.....	588,601
Heating furnace, Laughlin & Reuleaux.....	588,702
Heeling machine, J. H. Pope.....	588,936
Hinge, T. J. Goodwin.....	588,567
Hinge, E. C. Hoffman.....	588,642
Hinge for water closet seats and covers, C. F. Streit.....	588,720
Hinge, strap, J. H. Lawrence.....	588,925
Hoisting and tripping apparatus, W. S. Reese.....	588,756
Hoisting device, J. H. Hammer.....	588,827
Horse shoe attachment, W. J. Maier.....	588,937
Horse shoe, rubber tread, H. Schmid.....	588,734
Hose reel, garden, J. P. Casselman.....	588,897
Hub attaching device, S. J. Harry.....	588,863
Humidifying apparatus, O. Hoffmann.....	588,643
Hydrocarbon burner, G. C. Roberts.....	588,658
Incandescent lighting substance, W. Mahler.....	588,685
Indicator, See Liquid indicator. Order indica- tor. Speed indicator. Station indicator.....	
Injector, J. Friedmann.....	588,676
Insect exterminating machine, G. J. Moeller, Jr. Iron on steel, apparatus for pouring molten, G. W. Bierer.....	588,752 588,549
Jack, See Lifting jack.....	
Joint, See Rail joint. Railway rail joint.....	
Key register, electrical, W. Kraft.....	588,797
Key and door fastener, C. E. Smith.....	588,758
Kiln, Schlump & Honzik.....	588,885
Kinestoscope, Swain & Frost.....	588,916
Knee protector, A. Herbelin.....	588,907
Knitting machine needle dial, H. Eddishaw et al Knitting machine stop motion, circular, White & Sullivan.....	588,559 588,761
Knitting machine stop motions, automatic drop wire supply.....	588,762
Knob spindle fastener, A. O. Wynan.....	588,673
Lamp, bicycle, W. S. Hamm.....	588,904
Lamp burner, L. J. Atwood.....	588,788
Lamp, electric arc, B. F. Greene.....	588,822
Lamp, electric arc, T. Spencer.....	588,610
Lamp support, incandescent, E. L. P. Wetmore.....	588,890
Last, Mills & Mundell.....	588,718
Lasting machine, E. F. Grandy.....	588,568
Latch, H. Frohlich.....	588,639
Lath, metal, D. B. Hilton.....	588,574
Lathe, ball turning, D. Roche.....	588,914
Latrine, automatic flushing, I. D. Sinead.....	588,609
Lawn sprinkler, E. A. White.....	588,846
Lead from lead ore, making litharge or protoxide of, P. G. Salom.....	588,883
Leather cutting tool, G. E. Rank.....	588,928
Lever, controlling, A. L. Parsons.....	588,868
Lifting jack, F. P. Johnson.....	588,579
Liquor distributing tool, W. Lyon.....	588,770
Liquid indicator, automatic, F. A. Morse.....	588,650
Lock, See Time lock.....	
Lock, A. Fairhurst.....	588,561
Lock, C. C. Hovey.....	588,916
Log rolling and turning machine, G. M. Pelton.....	588,652
Log turner, G. M. Pelton.....	588,600
Loom picker stick bearing, H. M. Schadewald.....	588,690
Loom shuttle, A. Wood.....	588,935
Lubricating journals under pressure, apparatus for, C. E. For.....	588,690
Lubricator, H. Glanz.....	588,566
Manganate and producing same, E. B. Stuart.....	588,614
Meat cutting machine, C. W. Hinrichs.....	588,828
Meter, See Gas meter.....	
Meter, F. Lambert.....	588,646
Meters, mechanism for operating registering de- vices of, F. Lambert.....	588,924
Microscope attachment, E. Bausch.....	588,689
Mill, See Sawmill. Stamp mill. Windmill.....	
Mirror attachment for theater chairs, S. Walker.....	588,845
Mould, See Glass blower's mould.....	
Monkey wrench, M. E. Archer.....	588,906
Motor, See Wave motor.....	
Motor worked by hydrocarbon or other gases, C. T. Wordsworth et al.....	588,672
Nail puller, E. C. Fowler.....	588,744
Necktie fastener, A. B. Jones.....	588,864
Needle and needle filing machine, G. W. Ray- mond.....	588,836
Nursery chair, E. R. Sleeper.....	588,707
Nut lock, H. Schweitzer.....	588,661
Oil burner, T. R. Browne.....	588,691
Order indicator, W. H. Reynolds.....	588,805
Ore and making same, composition for making fine iron, J. J. Czepl.....	588,792
Organ, reed, F. D. Dexter.....	588,713
Oven, M. M. Williams.....	588,624
Over shoe, D. J. Fry.....	588,919
Oxygen and making same, compound for separa- ting, E. B. Stuart.....	588,613
Oxygen and nitrogen, from air, obtaining, E. B. Stuart.....	588,617
Oxygen, process of and compound for separating, E. B. Stuart.....	588,615
Oxygen separating compound and making same, E. B. Stuart.....	588,616
Package for laundered or other articles, W. E. Locke.....	588,587
Packing, steam, P. F. Leary.....	588,681
Padlock, L. H. Pennepacker.....	588,654
Paper bag machine, H. Salmon.....	588,782
Paper folding machines, header up device for, T. C. Dexter.....	583,694
Pavement, illuminating area spanning, P. M. Bruner.....	588,725
Pen attachment, J. G. Jordan.....	588,865
Pen, fountain, W. W. Stewart.....	588,708
Pencil, G. H. Knight.....	588,787
Perfumes, making, M. Eikenberg.....	588,766
Photographic background carrier, L. C. Over- peck.....	588,597
Photographic films, method of and apparatus for making, Blair & Waterman.....	588,790
Piano damper action, grand, A. N. Kinkel.....	588,594
Pin, See Drapery pin. Safety pin.....	
Pin, H. C. Conkle.....	588,675
Pipe wrench, P. W. Lowmes.....	588,751
Pipes, cigar holders and cigarette holders, attach- ment for, J. J. Lynch.....	588,869
Plow, bedding, E. C. Atkins.....	588,787
Plow harrow attachment, W. S. Payne.....	588,845
Post hole digger, H. L. T. Overbey.....	588,833
Potato digger and plow, convertible, D. Y. Hal- lock.....	588,826
Power, electrical transmission of, E. Lanboffer.....	588,831
Power, mechanism for transmitting motive, C. T. Wordsworth et al.....	588,625
Press, See Glass press. Seal press.....	
Printing device, Bentley & Schiek.....	588,853
Printing press delivery device, S. G. Goss.....	588,728
Printing press gripper, job, R. Campbell.....	588,895
Prison cell, vault, etc., Peterhansl & Rothmann.....	588,834
Pulley, See Nail pulley.....	
Pulley, expandible, F. I. Dana.....	588,896
Pump, J. A. Fink.....	588,918
Puzzle, E. Nelson.....	588,705
Puzzle, L. G. Warner.....	588,688
Radiator, oil, H. Ruppel.....	588,780
Rail bond, electric, W. B. Cleveland.....	588,791
Rail joint, E. Norton.....	588,586
Railway crossing, C. E. Baker.....	588,789
Railway crossing, A. H. Tyler.....	588,737
Railway rail joint, A. W. Thompson.....	588,807
Railway rails, electric connection between, F. Marshall.....	588,771
Railway switch, C. F. Kress, Jr.....	588,581
Razor guard, H. T. Fisher.....	588,564
Reaping machine, M. Alexandrescu.....	588,850
Reel, See Hose reel.....	
Refrigerator, E. Sack.....	588,781

(Continued on page 159)

Chain BELTING of Various Styles, ELEVATORS, CONVEYORS, COAL MINING and HANDLING MACHINERY.
The JEFFREY MANUFACTURING CO., COLUMBUS, O.
Send for late Catalogue "C." Branches: CHICAGO—NEW YORK.

Phonographs, Graphophones, Projectoscopes, Kinetoscopes, RECORDS, FILMS, ETC.
36 page illustrated catalogue sent free on receipt of 2-cent stamp.
The Edison Phonograph Co., 427 Vine St., Cincinnati, O.

R. POOLE & SON CO.
ENGINEERS, FOUNDERS AND MACHINISTS.
BALTIMORE, MD.
MANUFACTURERS AND DESIGNERS OF ALL KINDS OF
HEAVY MACHINERY.
REQUIRING FIRST CLASS WORKMANSHIP AND MATERIALS.
BAND ROPE, ANGLE WHEELS, FRICTION CLUTCHES, PULLEYS, MACHINE MOLDED SHAFTING AND PLANED GEARING.
POOLE-LEFFEL TURBINE WATER-WHEELS.
CIRCULARS ON APPLICATION.

CROOKES TUBES AND ROENTGEN'S
Photography.—The new photography as performed by the use of Crookes tubes as a source of excitation. All about Crookes tubes. SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 181, 189, 238, 243, 244, 792, 793, 905, 980, 1050, 1054, 1055, 1056, 1057, also SCIENTIFIC AMERICAN, Vol. 74, No. 14, Vol. 74. These profusely illustrated SUPPLEMENTS contain a most exhaustive series of articles on Crookes tubes and the experiments performed with them. Among them will be found Prof. Crookes' early lectures, detailing very fully the experiments which so excited the world and which are now again exciting attention in connection with Roentgen's photography. Price 10 cents each. To be had at this office and from all newsdealers.

A New Adjustable VACUUM TUBE.
Automatic control of the Vacuum Positive. Write for particulars to SWETT & LEWIS CO., Manufacturers of X Ray Supplies, 11 Bromfield St., Boston, Mass.

WATER MOTORS
GAS ENGINES & VENTILATING FANS
The best Motor in the world for driving all kinds of light machinery, noiseless, neat, compact; invaluable for blowing church organs, running printing presses, coffee mills, ventilating fans, ice cream freezers, meat choppers, etc. In use by the world over, and recommended by water companies everywhere. Address for circulars, Backus Water Motor Co., Newark, N. J., U. S. A.

STEREOPTICONS, MAGIC LANTERNS
and all accessories for School and Church Entertainments and adult and juvenile amusement and instruction.
Microscopic instruments for physicians and all professional uses. Send for free illustrated catalogue to CHAS. BESELER, Established 1882, Patentee and Manufacturer, 216 Centre Street, New York, N. Y.

WE ARE RELIABLE MAKERS OF HIGH GRADE Stereopticons and Magic Lanterns
lime and oil light arranged for electric light instruments, etc., are guaranteed perfect before leaving our factory. Write to PETERS, MANTZ & CO., (many years with the late Mr. Chas. Beseler), 125 and 127 Worth Street, New York City.

THE NEW BRISTOL COUNTER
Registers an accurate account of work done on printing presses, grain tallies, weighing, measuring and other automatic machines. Counts up to 1,000,000 and repeats automatically. Simple, accurate, durable. Special counters for order. Send for circular to C. J. ROOT, Bristol, Conn., U. S. A.

IMPROVED WASHBURN'S PATENT CUFF HOLDER AND DRAWERS SUPPORTER.
A Cuff Holder that holds the cuff just where you want it. No button holes needed. No tearing of shirt or cuff. Drawers supporters that are easily adjusted or taken off. Hold tight, hurt nothing, and save annoyance. Sample of either of the above, by mail, for 10 cents. Illustration free.
American Ring Co., Dept. S. A., Waterbury, Ct.

Why Make Rubber Stamps?
Our "New York" Rubber Stamp Vulcanizers received the only medal awarded any Vulcanizer, World's Fair, Chicago. Simple process. Large profits. Circulars free.
BARTON MFG. CO., 338 Broadway, New York, U. S. A.

USE GRINDSTONES?
If so, we can supply you. All sizes mounted and unmounted, always kept in stock. Remember, we make a specialty of selecting stones for all special purposes. Ask for catalogue.
The CLEVELAND STONE CO.
2d Floor, Wilshire, Cleveland, O.

HYPNOTISM
Easy mail course for Investigators, Exhibitors, Lecturers, and Healers. Valuable information and illustrated booklet on request. Prof. Anderson, S. A. 97, Masonic Temple, Chicago

THE CHICAGO DRAINAGE CANAL.
Description of a great engineering work undertaken to prevent the contamination of the city's water supply. With 6 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1017. Price 10 cents. To be had at this office and from all newsdealers.

NO MORE "POISON IN THE BOWL"
No excuse for smoking foul pipes. The "Mallinckrodt" Patent Nicotine Absorbent and Ventilated Tobacco Pipe will render smoking a healthy enjoyment. Try it and you will become convinced. See notice, SCI. AM. of August 7, '97. Manufactured only by The Harvey & Watts Co., Station E, Philadelphia, Pa. and No. 275 Canal Street, New York. Illustrated Circulars "S. A." mailed on application.

MODEL WORK
We are prepared to assist the trade and inventors in solving mechanical problems, also manufacturing models and stock.
CENTURY MACHINE CO., 576 W. Broadway, New York
Complete outfit of modern machinery and tools.

IT COSTS NOTHING TO TRY!
All steam users can save time money and trouble with the simplest, safest and most satisfactory trap in existence—the HEINTZ STEAM TRAP. Guaranteed never to wear out. Look at the cut and see how it's done! Pay me what you save in coal for one year and I'll furnish the trap free. See illus. notated. An July 31, 1897. Sole American Agent, Wm. S. Haines, 8 136 S. 4th St., Phila., Pa.

MANUFACTURE OF STARCH FROM Maize.—By J. Krieger. Full details of the process. With one illustration. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1012. Price 10 cents. To be had at this office and from all newsdealers.

Watchman's Improved Time Detector
with 12 or 24 Keys, with Safety Lock attachment. Patented 1875-6-7. My inventions, and will sue all concerns selling or using the Safety Lock attachment, according to Decision of Circuit Court of U. S. for S. D. of N. Y. Send for circulars to EL. IMHAUSER, 206 Broadway, New York. P. O. Box 285.

EDGE TOOLS
are often nearly ruined by using a grindstone not adapted to the work. Our quarries produce a large variety of grinds suitable for grinding any tool. May we send you our Catalogue, which will give you some information?
GRAFTON STONE COMPANY,
No. 80 River Street, Grafton, Ohio

Headquarters for DUMPING HORSE CARTS.
Wide and narrow tires. Low rates of freight from our works—Tatamy, Pa.—to all points.
HOBSON & CO.
No. 4 Stone St., New York.

Experimental Science
By GEO. M. HOPKINS.
17th Edition Revised and Enlarged.

EXPERIMENTAL SCIENCE
840 pages, 782 fine cuts, substantially and beautifully bound. Price in cloth, by mail, \$4. Half morocco, \$5.
This splendid work is up to the times. It gives young and old something worthy of thought. It has influenced thousands of men in the choice of a career. It will give anyone, young or old, information that will enable him to comprehend the great improvements of the day. It furnishes suggestions for hours of instructive recreation.
Send for illustrated circular and complete table of contents. . . .
MUNN & CO., Publishers,
Office of the . . .
SCIENTIFIC AMERICAN,
361 BROADWAY, - NEW YORK.

Nearly Ready.

MAGIC

Stage Illusions and Scientific Diversions
Including Trick Photography.

COMPILED AND EDITED BY
ALBERT A. HOPKINS.

WITH AN INTRODUCTION BY
HENRY RIDGELY EVANS.

Over 500 pages. Over 400 illustrations.

This is a new and unique work on magic art. It contains exposés of the sleight-of-hand feats and illusions of the most famous conjurers of modern times. It is profusely illustrated with over 400 engravings. The subjects treated include interesting Biographies of Celebrated Conjurers, the Mysteries of Modern Magic, Ancient Magic, Science in the Theater, Automata, Curious Toys, and Photographic Diversions. The very latest developments in each line will be given. Thus, under photography the projection of moving pictures is taken up for the first time in book form.

An illustrated circular of this work is now ready, and will be mailed on request to any part of the world. The book will be sent, postpaid, on receipt of \$2.50.

MUNN & CO., PUBLISHERS,
361 BROADWAY, NEW YORK CITY.

WOODEN TANKS.
For Railroads, Mills and Manufactories.
Builders of Steel Towers and Tanks.
La. Red Cypress Wood Tanks a specialty.
W. E. CALDWELL CO.,
217 E. Main Street, Louisville, Ky.

ELECTRO MOTOR, SIMPLE, HOW TO MAKE.—By G. M. Hopkins. Description of a small electro motor devised and constructed with a view to assisting amateurs to make a motor which might be driven with advantage by a current derived from a battery, and which would have sufficient power to operate a foot lathe or any machine requiring not over one man power. With 11 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 641. Price 10 cents. To be had at this office and from all newsdealers.

SO SIMPLE A CHILD CAN USE THEM
SUNART
MAGAZINE CAMERA.
Folding Cameras.
All sizes, ranging in price from \$5 to \$100. Sunart Junior, 3 1/2 x 5 1/2 picture, \$5.
Send 2 cent stamp for Illustrated Catalogue.
SUNART PHOTO CO.
5 AQUEDUCT STREET, ROCHESTER, N. Y.

DRY BATTERIES.—A PAPER BY L. K. BOHM. treating of open circuit batteries, historical dry batteries, modern dry batteries, Hellen's battery, Bryan's battery, Koller's battery, and the efficiency of dry cells. With three illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1001. Price 10 cents. To be had at this office and from all newsdealers.

ELECTRIC STOVE.
Enamelled slate base. Hot in two minutes. Emerges cooking or heating—always ready. Price \$5.00.
Complete, ready for use, with cord and plug. Give make of lamp socket and voltage.
AMERICAN ELECTRIC HEATING CORPORATION.
BRANCH OFFICES: Havemeyer Bldg., New York. Monadnock Bldg., Chicago.
GENERAL OFFICE: Sears Building, BOSTON.

Drying Machines
for Grain, Sand, Clays, Fertilizers, Phosphates, Green Coffee, Wet Feeds, Salt, Sugar, Chemicals, etc. 15 Years in operation. Send for 80 illustrated catalogue.
S. E. WORRELL, Hannibal, Mo.

Twelfth Edition Now Ready.

THE SCIENTIFIC AMERICAN CYCLOPEDIA OF Receipts, Notes and Queries

12,500 RECEIPTS. 708 PAGES.
Price, \$5.00 In Cloth; \$6.00 In Sheep; \$6.50 In Half Morocco, Postpaid.


THIS great work has now been on the market for nearly six years, and the demand for it has been so great that twelve editions have been called for. It is entirely distinct from the ordinary receipt book in being thoroughly up to date.

The work may be regarded as the product of the studies and practical experience of the ablest chemists and workers in all parts of the world; the information given being of the highest value, arranged and condensed in concise form, convenient for ready use. Almost every inquiry that can be thought of, relating to formulae used in the various manufacturing industries, will here be found answered.

Those who are engaged in almost any branch of industry will find in this book much that is of practical value in their respective callings. Those who are in search of independent business or employment, relating to the home manufacture of salable articles, will find in it hundreds of most excellent suggestions.

Send for descriptive circular.

MUNN & CO., Publishers,
361 Broadway, New York.



Refrigerator, cleanable, Smith & Atherton	588,664
Register. See Cash register. Keg register.	
Register foot rest, C. M. Dechant	588,683
Regulator. See Windmill regulator.	
Rope fastener, W. T. Gillen	588,903
Ruler plumb and level attachment, E. D. Beatty	588,552
Safety pin, J. Phillips	588,778
Sand band, J. L. Freasier	588,818
Sash cord fastener, E. W. Phillips	588,730
Saw mill, band, G. M. Pelton	588,653
Scale beam, computing, W. R. Dunn	588,857
Scale, spring balance computing, G. B. & F. C. Hoyt	588,748
Scraper, road, T. R. McKnight	588,753
Scrubbing and mopping machine, J. Ledwon	588,584
Seal, bottle, Heath & Nagell	588,575
Seal press, portable, T. J. Parkinson	588,327
Sewing machine attachment, J. H. Gaskins	588,677
Sewing machine table or cabinet, T. Kund	588,738
Shade holder, M. D. Greengard	588,570
Shade roller support, A. F. Wahlberg	588,571
Shafts, means for supporting rotating, Stanley & Darlington	588,710
Ship cleaning device, electrically operated, E. T. Thomas	588,666
Shoe, J. E. Kennedy	588,933
Shoelining, machine for marking, L. T. Adams	588,786
Show case, plate glass, A. Moorman	588,647
Sickle, J. C. H. Vaught	588,843
Sifter, ash, A. Haenichen	588,745
Slipshoe, pinkish, J. S. Yager	588,751
Soldering machine, can, N. M. Bain	588,819
Sole, shoe, J. E. Kennedy	588,788
Spacing mechanism, Lewis & Ramsden	588,799
Speed indicator, W. S. Scales	588,351
Spinning ring, G. O. Draper	588,817
Sprinkler. See Lawn sprinkler. State sprinkler.	
Stacker, straw, W. A. Hinkle	588,910
Stamp mill, G. M. Ross	588,906
Stamping apparatus for tickets, date and time, C. C. Van Der Valk	588,668
Station indicator, Colman & Myers	588,835
Station indicator for tramway or other cars, Langschmidt & Le Brocq	588,701
Stock guard, J. M. Lee	588,868
Stone dressing machine, D. W. Darling	588,634
Stool, folding and extensible piano, J. W. Stanton	588,932
Stool, shoe, Sawyer & Harris	588,607
Stopper. See Bottle stopper.	
Stove, J. P. Pool	588,755
Stove, cooking and heating, H. D. Sawyer	588,884
Stove cooking attachment, G. B. Dunstan	588,696
Stove grate, E. E. Flint	588,859
Stove griddle, J. E. Gattley	588,819
Swaging machine, A. J. Morse	588,648
Switch. See Railway switch.	
Sirup, manufacturing beet root, F. H. Werner	588,623
Tablet, sleeve, F. A. Carlson	588,553
Tank. See Watering tank.	
Tanning or tawing skins, W. M. Norris	588,874
Thermometer, clinical, J. J. Hicks	588,796
Thrasher and separator, combined, F. E. McNail	588,903
Threshold, C. Baumann	588,626
Tie. See Bag tie.	
Time lock, J. G. Blake	588,627
Tire, W. B. Greedy	588,823
Tire, bicycle, C. J. Bailey	588,724
Tire, epicycular, W. N. Murdock	588,872
Tire inflator in cycle framework, H. D. Simpson	588,840
Tire, pneumatic, W. I. Dreisbach	588,557
Tire, pneumatic, H. J. La Force	588,680
Tire, pneumatic, C. E. Johnson	588,623
Tire, vehicle wheel, J. M. Farmer	588,562
Toe blank, box, I. H. Fish	588,638
Tongue bar supporting clamp, J. H. Moyer	588,687
Tool, J. M. Rauhoff	588,879
Toothpick making machine, Lamb & Bales	588,645
Toy gun or catapult	588,842
Track brake, J. U. Elwood	588,858
Track cleaning device, rotary, G. W. Baehre	588,711
Traction engine, C. Quast	588,877
Tripod, F. A. Brownell	588,552
Trolley and railway, suspension, A. Huber	588,714
Trolley wire hanger, C. E. Johnson	588,623
Truck bolster, Fries & Casey	588,777
Truck, car, J. C. Barber	588,810
Truck frame, railway car, G. R. Joughins	588,580
Trunk, wardrobe, E. M. Thomas	588,721
Truss, S. Ide	588,578
Tube or hose, J. Watson	588,842
Tug attachment, same, J. Mealey	588,589
Typewriting machine, F. A. Heiss	588,746
Typewriting machine, W. S. Shirk	588,608
Umbrella or parasol, F. H. Mitchell	588,773
Valve, check, H. Keimach	588,779
Valve gear, pneumatic, C. E. Johnson	588,623
Valves, electrical indicator for, W. J. Rickard	588,880
Vegetable cutter, J. F. Rote	588,606
Vehicle spring, Blum & Anderson	588,813
Velopede driving gear, Macmahon & Postans	588,694
Voting machine, G. Wilson	588,671
Wagon brake, C. Garcke	588,842
Wagon, dumping, W. Rodenhausen	588,882
Washing machine, H. B. Roach	588,604
Water elevator, pneumatic, J. Haas	588,825
Water tube boiler, W. Sellers et al.	588,839
Watering tank, C. E. Irwin	588,716
Wave motor, F. Harding	588,641
Weight indicating device, D. K. Simonds	588,719
Wheel. See Carriage wheel. Fifth wheel.	
Windmill, R. E. Hardaway	588,572
Windmill regulator, H. Barthels	588,548
Window, sliding and swinging, F. Faerber et al.	588,700
Wine gasifying apparatus, C. Ameye	588,547
Wire stretcher, J. J. Brooks	588,741
Wire stretcher, Z. F. Howard	588,921
Wiring the edges of covers, etc., mechanism for, H. H. Hull	588,749
Wood bending machine, Burgett & Brown	588,743
Wrapper for fruit or vegetables, C. M. Brown	588,680
Wrench. See Monkey wrench. Pipe wrench.	
Writer's cramp, device for preventing, Einfeldt & Brace	588,902

DESIGNS.

Basket, J. O. Neel	27,574
Bicycle, J. W. I. Grubb	27,576
Bicycle saddle seat, H. A. Christy	27,577
Bracket, crank bearing, C. W. Dake	27,576
Carpet, J. Merry	27,580
Coin actuated wheels, casing and support for, W. H. Catell	27,579
Guitar body, J. S. Bak	27,581
Guitar body, F. F. Hark	27,580
Hat support, H. G. Cozzino	27,558
Ice shave, Foster & Coleman	27,573
Mandolin body, E. F. Howe	27,559
Nail puller fulcrum shoe, C. A. Maynard	27,571
Plate and container, J. J. Becker	27,564
Plate or analogous article, L. S. Ipsen	27,562
Rivet, W. C. Bray	27,567
Sash fastener lever, G. M. Hubbard	27,572
Soap coke or bar, W. G. Webb	27,556
Stay cover, dress, C. Sisson	27,557
Tack or nail, F. A. Bokar	27,570
Toy safe, C. A. Bailey	27,566
Toy savings bank, P. Adams	27,565
Wrenches, movable jaw for, J. C. Ives	27,575

TRADE MARKS.

Beer, J. & P. Baltz Brewing Company	30,511 to 30,513
Beer, dark lager, Weisbrod & Hess	30,514
Benzoic sulfid or benzoic sulfid combined with sodium oxid, pure and refined, Fahlerberg, List & Company	30,524
Buttons, pearl, A. Frey & Company	30,508
Canned fruits, W. B. Dudley	30,520 to 30,522
Canned goods, certain named, Portland Packing Company	30,523
Coffee, cereal, Climax cereal Coffee Company	30,517
Drink of special preparation, cereal warm, Our Home Granula Company	30,516
Flour, firm of G. T. Evans	30,518
Forks, hoes, shovels and rakes, agricultural and other, Otego Fork Mills Company	30,526
Gelatin, Groat & Groat	30,519
Gum, chewing, Wetmore & Friedman Manufacturing Company	30,510
Hooks and eyes, buttons, pins, buckles and similar garment fasteners, Sweet Brothers	30,509
Leather and imitation leather upholstery goods and fringe, M. Rosenfeld & Company	30,506
Lemon juice, preserved, J. D. Lehmer	30,515
Launs and cotton goods, Solingen & Company	30,505
Pipe cleaners, mechanical, J. Craig, Jr.	30,525

A printed copy of the specification and drawing of any patent in the foregoing list, or any patent in print issued since 1883, will be furnished from this office for 10 cents. In ordering please state the name and number of the patent desired, and remit to Munn & Co., 361 Broadway, New York. Special rates will be given where a large number of copies are desired at one time.

Canadian patents may now be obtained by the inventors for any of the inventions named in the foregoing list, provided they are simple, at a cost of \$40 each. If complicated the cost will be higher. For full instructions address Munn & Co., 361 Broadway, New York. Other foreign patents may also be obtained.

MURRAY
Our New Catalogue contains 260 pages of bargains. Single Buggy
Harness \$3.90; Double Buggy Harness \$12.75; Road Wagons \$19.95; Top Buggies \$29.85; Road Carts \$8.90; Phaetons, Surreys, Spring Wagons, Delivery Wagons, Milk Wagons, Farm Wagons & everything on wheels at prices never before heard of.
If interested, send for free catalogue No. 3.
WE SELL DIRECT TO THE CONSUMER
WILBER H. MURRAY MFG CO.
CINCINNATI, OHIO, U.S.A.
PRICE \$13.80 MURRAY ROAD CART
PRICE \$29.85 MURRAY TOP BUGGY
PRICE \$54.90 MURRAY PHAETON
PRICE \$3.90 MURRAY HARNESS

CAUSE OF LUMINOSITY IN THE
Flames of the Hydrocarbon Gases.—By Prof. Vivian B. Lewes. An important paper in which the author endeavors to show that the luminosity of hydrocarbon flames is due to the localization of the heat of formation of acetylene in the carbon and hydrogen produced by its decomposition, and the cause of such localization. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 1012 and 1013. Price 10 cents each. To be had at this office and from all newsdealers.

Buy Telephones
THAT ARE GOOD—NOT "CHEAP THINGS."
The difference in cost is little. We guarantee our apparatus and guarantee our customers against loss by patent suits. Our guarantee and instruments are both good.
WESTERN TELEPHONE CONSTRUCTION CO.
250-254 South Clinton St., Chicago.
Largest Manufacturers of Telephones exclusively in the United States.

THE CARBIDES AND ACETYLENE
Commercially Considered.—By T. J. Willson and J. J. Suckert, Ph.D. A consideration of the carbides and acetylene from a commercial point of view, preceded by a brief history of these compounds, the methods of their formation, and their chemical and physical properties. With 10 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 1015 and 1016. Price 10 cents each. To be had at this office and from all newsdealers.

TUBULAR DRIVING LAMP.
IT is the only perfect one.
IT will not blow or jar out.
IT gives a clear, white light.
IT is like an engine head-light.
IT throws the light straight ahead from 200 to 300 ft.
IT burns kerosene.
Send for book (free).
R. E. DIETZ CO., 60 Laight Street, New York.
Mention this paper and get special discount.
—ESTABLISHED 1840—

WORKING MODELS of all kinds designed and perfected. Secrecy guaranteed. J. C. Seyl, 181 Madison St., Chicago.

THE COPYING PAD.—HOW TO MAKE
and how to use; with an engraving. Practical directions how to prepare the gelatine pad, and also the aniline ink by which the copies are made, how to apply the written letter to the pad, how to take off copies of the letter. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 428. Price 10 cents. For sale at this office and by all newsdealers in all parts of the country.

Electrical Novelties
Hand Power Dynamo, - - \$6.50
Water Motor Dynamo, - - 8.00
Electric Railways, \$3.50 and 6.50
Stamp for catalogue of other novelties.
THE CARLISLE & FINCH CO.
Sixth Street, Cincinnati, Ohio

BRASS BAND
Instruments, Drums, Uniforms, Equipments for Bands and Drum Corps. Lowest prices ever quoted. Fine Catalog, 400 Illustrations, mailed free; it gives B and Music & Instructions for Amateur Bands.
LYON & HEALY, 33-35 Adams St., Chicago.

NICKLE PLATING WANTED
ORDER EXECUTED IN ANY QUALITY OR QUANTITY.
BETTS & MABBETT CO.
29 NORTH WASHINGTON ST., ROCHESTER, N.Y.

THE SANDBLAST PROCESS.—BY J. J. Holtzapfel. A full description of this interesting process and of the apparatus employed; with a discussion of its capabilities and present and future applications. With 8 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1010. Price 10 cents. To be had at this office and from all newsdealers.

ON A STILL HUNT.
The up-to-date sportsman needs for success, personal comfort, and protection the **ideal Hunting Shoe**.
Tanned horsehide, uppers gray color, soft as a glove, tough as steel, cannot harden. Wide double soles, rubber cemented together. Practically waterproof, flexible, easy. The most serviceable shoe for surveyors and engineers. *Illustr. circulars free.*
A. SMITH & SONS
Manufacturers, 29-31 N. 13th Street, Philadelphia.
SPORTING SHOES OF ALL KINDS.

How to Build a Home



Those intending to build will find the very best practical suggestions and examples of Modern Architecture in the handsomest Architectural Magazine ever published . . .
"The Scientific American Building Edition."
Each number is illustrated with a Colored plate and numerous handsome engravings made direct from photographs of buildings, together with interior views, floor plans, description, cost, location, owners' and architects' names and addresses. The illustrations include seashore, southern, colonial and city residences, churches, schools, public buildings, stables, carriage houses, etc.
All who contemplate building, or improving homes or structures of any kind, have in this handsome work an almost endless series of the latest and best examples from which to make selections, thus saving time and money.
PUBLISHED MONTHLY. SUBSCRIPTIONS \$2.50 A YEAR. SINGLE COPIES 25 CENTS.
For sale at all news stands, . . . or address **MUNN & CO., Publishers, 361 Broadway, New York**

FILMS For the Best Projectorscope or Kinetoscope Films, new list. F. L. WILLARD, 106 Lexington Avenue, Brooklyn, N. Y.

Experimental Pattern and Model Work, Optical, etc., Instruments, bicycle sundries. EMPIRE NOVELTY WORKS, 402 E. 30th St., New York.

ICE MACHINES, Corliss Engines, Brewers' and Bottlers' Machinery. THE VILTER MFG. CO., 899 Clinton Street, Milwaukee, Wis.

MODELS & GEARS CATALOGUES FREE UNION MODEL WORKS 193 CLARK CHICAGO.

Shorthand by Mail Thoroughly taught by re- lession Free. Potts Shorthand College, Williamsport, Pa.

SPECTACLES F. E. BAILEY sells spec cheap. Write for new optical catalogue. 271 Wabash Ave., Chicago.

DEAFNESS & HEAD NOISES CURED. Our INVISIBLE TUBE Cushions help when all else fails as glasses help eyes. NO PAIN. Whispers heard. Send to F. Hiseox (Co., 85-B E'way, N. Y., for Book and Proof. FREE

MODEL AND EXPERIMENTAL WORK Draughting, Pattern Work, Special Machinery, etc. S. P. Demison, 143 Center St., New York City

TYPE WHEELS, MODELS & EXPERIMENTAL WORK, SMALL MACHINERY NOVELTIES & ETC. NEW YORK STENCIL WORKS 100 NASSAU ST. N.Y.

WANTED—American Specialties for introduction throughout Germany. Correspondence solicited. Address H. DIEZ, care of H. G. Ramsperger & Co., 180 Pearl Street, New York.

STEEL STAMPS FOR MARKING TOOLS FIGURE & ALPHABET SETS AT LOWEST PRICES. BEST STEEL. GUARANTEED. SEND FOR CIRCULAR. **SCHWAAB STAMP & SEAL CO.** MILWAUKEE, WIS.

VOLNEY W. MASON & CO., Friction Pulleys, Clutches & Elevators PROVIDENCE R. I.

STRONG CASTINGS. QUICK DELIVERY. PATTERN WORK TO ORDER. ACME MALLEABLE IRON WORKS. BUFFALO, N.Y.

AMERICAN PATENTS.—AN INTER-esting and valuable table showing the number of patents granted for the various subjects upon which petitions have been filed from the beginning down to December 31, 1884. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1002. Price 10 cents. To be had at this office and from all newsdealers.

50 YEARS' EXPERIENCE.
PATENTS
TRADE MARKS, DESIGNS, COPYRIGHTS &c.
Anyone sending a sketch and description may quickly ascertain, free, whether an invention is probably patentable. Communications strictly confidential. Oldest agency for securing patents in America. We have a Washington office. Patents taken through Munn & Co receive special notice in the
SCIENTIFIC AMERICAN, beautifully illustrated, largest circulation of any scientific journal, weekly, terms \$3.00 a year; \$1.50 six months. Special rates for copies and HAND BOOK ON PATENTS sent free. Address
MUNN & CO., 361 Broadway, New York.

Preserve Your Papers.
Subscribers to the SCIENTIFIC AMERICAN and SCIENTIFIC AMERICAN SUPPLEMENT, who wish to preserve their papers for binding, may obtain the Koch Patent File at the office of this paper. Heavy board sides, inscription "Scientific American" and "Scientific American Supplement" in gilt. Price \$1.50, by mail, or \$1.25 at this office. Address
MUNN & CO., 361 BROADWAY, NEW YORK

Advertisements.

ORDINARY RATES.

Inside Page, each insertion, - 75 cents a line
Back Page, each insertion, - \$1.00 a line
For some classes of Advertisements, Special and Higher rates are required.

The above are charges per agate line—about eight words per line. This notice shows the width of the line, and is set in agate type. Engravings may head advertisements at the same rate per agate line, by measurement, as the letter press. Advertisements must be received at Publication Office as early as Thursday morning to appear in the following week's issue.

To Inventors and Manufacturers!

I have unusual facilities for Working or Placing Valuable Patents in United States, Great Britain, and other foreign countries. Correspondence invited.
E. C. MILLER, care MAGNOLIA METAL CO.,
266 & 267 West Street, New York

You Often Hear

people say "there are others," but they usually add "we know Columbias are the best." There never was a truer acknowledgment of Columbia superiority. At the present prices there is no reason why you should not join the army of Columbia riders.

1897 Columbia Bicycles

STANDARD OF THE WORLD. \$75 to all alike.

1897 Hartfords,	50
Hartfords, Pattern 2,	45
Hartfords, Pattern 1,	40
Hartfords, Patterns 5 and 6, . .	30

POPE MFG. CO., HARTFORD, CONN.
If Columbias are not properly represented in your vicinity, let us know.

The \$5.00

Falcon Camera

FOR 3½ x 3¼ PICTURES.



Uses our
Light-Proof
Film Cartridges
For 12
Exposures and
LOADS IN
DAYLIGHT.

Improved safety shutter, set of three stops, fine achromatic lens, view finder and socket for tripod screw. *Booklet Free.*

\$2,853.00 in Prizes
For Kodak Pictures.
\$1,475.00 in Gold.


EASTMAN KODAK CO.
ROCHESTER, N. Y.

It has Simplified Photography.


Made to open in broad daylight for loading and adjustment.

The Adlake Camera

Complete with 12 light-tight metal plate holders, prepaid to any part of the United States for . . . \$12
Takes 12 Pictures on dry plates at one loading.
Standard Size 4 x 5 inches. "No Extras."
Get your plates anywhere.



Ask your photo stock dealer to get you an "Adlake" for inspection. Our "Adlake Camera Book" tells all about it. Free for the asking. Sample mounted photograph 6 cents in stamps.
The Adams & Westlake Co., 108 Ontario St., Chicago



The high standing and long experience of the following

Gold AND Silver Miners

"THE GRIFFIN MILL."

"We have concluded to order 10 more Griffin Mills. We have tried high-speed rolls and dry stamps, and after looking into the Huntington Dry Pulverizer, the Nord Pulverizer, the Stedman Pulverizer, the Frisbee-Lucop, the Cook, and various other dry pulverizers, unhesitatingly recommend your Griffin Mill to any one."

"The four Griffin Mills purchased of you for the firm of Ramon C. Ortiz, successor, of this city, are running successfully, and to the entire satisfaction of the owners. We have ground the 'dumps' of the old Quebedilla Spanish Silver Mine, and it is the hardest ore I ever saw. The Mills will average 20 tons each per day of 24 hours at a speed of only 180 revolutions per minute, and I am confident when speeded to 200 revolutions their capacity will be very materially increased."

"We have had one of your Griffin Mills in operation at our mill in Breckenridge, and we are well pleased with its operation. It crushes from 40 to 50 tons of our ore per day. We have used stamp and other mills, and are satisfied that the Griffin Mill is superior to any other of which we have any knowledge."

We will gladly send any interested person our pamphlet containing full description of The Griffin Mill and much other information regarding its demonstrated successes as a pulverizer of all refractory substances.

BRADLEY PULVERIZER CO., 92 State St., Boston.

THOROUGH INSPECTIONS
AND
INSURANCE
AGAINST LOSS
OR
DAMAGE
TO
PROPERTY
AND
LOSS-OF-LIFE
AND
INJURY
TO PERSONS
CAUSED BY
STEAM-BOILER-EXPLOSIONS
J. M. ALLEN, PRESIDENT W. B. FRANKLIN, VICE PRESIDENT
J. B. PIERCE, SECRETARY F. B. ALLEN, 2ND VICE PRESIDENT

THE Motor of 19th Century
Used ANY PLACE, BY ANYONE, FOR ANY WORK.
No fire! No boiler! No danger! No ashes! No danger!
ECONOMY, RELIABILITY, SIMPLICITY, SAFETY. Cost of operation about 1 Cent an hour to each indicated H. P.
Catalogue, Testimonials, etc., by addressing
CHARTER GAS ENGINE CO., Box 148, STERLING, ILL.

BUILT LIKE A WATCH
ROVND THE WORLD THE STERLING WINS ITS WAY
STERLING CYCLE WORKS
CHICAGO, ILL.

HALF A CENTURY OF CYCLES.—AN interesting history of the cycle from its origin up to the present time. The first crank-driven bicycle. The "bone-shaker" and its successors. The tricycle. The modern wheel. Cycle building a science. Points of improvement. The pneumatic tire. A hand and foot cycle. With 9 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1012. Price 10 cents. To be had at this office and from all new dealers.

JESSOP'S STEEL THE VERY BEST FOR TOOLS, SAWS, ETC.
WM. JESSOP & SONS, 12 91 JOHN ST. NEW YORK

Experimental & Model Work
Ours and advice free. Gardam & Son, 45-51 Rose St., N.Y.

HELMET OIL LUBRICATES ANYTHING IF YOU HAVE A HOT BOX
CH. B. SLY & CO. CHICAGO-ILL-USA

\$50 Worth of . . . Electrical Apparatus Including a Dynamo sent FREE
With our Complete Electrical and Mechanical Course, until September 30. This is not a prize offer. This apparatus is required by all students. They have hitherto had to pay extra for it. We will, for a short time, give it FREE to those who enroll. Our 72-page Catalogue, sent free to any address, explains.
Institute for Home Study of Engineering, 220 Seneca St., Cleveland, O.

BALL BEARING AXLES AND RUBBER TIRES.—A paper read before the Carriage Builders' National Convention, Philadelphia, October, 1884, showing the advantage to be derived from the use of ball bearings and pneumatic tires in road vehicles. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 992. Price 10 cents. To be had at this office and from all new dealers.


IMPERIAL BALL BEARING AXLE
A written guarantee with each set of axles.
97 PATTERN
8,000 sets in use. Indorsed by the leading carriage builders. Reduces friction 75 per cent. One horse can do the work of two. Mechanically perfect. Can be put on old or new work.
Write for our Illustrated Catalogue and Testimonials, which we send free on application. Imperial Ball Bearing Axle Dept., 439 Wabash Avenue, Chicago, Ill.

H. W. JOHNS' STEAM PACKING
Boiler Coverings, Millboard, Roofing, Building Felt, Liquid Paints, etc.
DESCRIPTIVE PRICE LIST AND SAMPLES SENT FREE.
H. W. JOHNS MFG CO., 100 William St., New York.

X Ray Tubes
WITH AUTOMATIC ADJUSTABLE VACUUM ATTACHMENT.
Impossible to run too high in vacuum. Life prolonged indefinitely.
Roentgen Ray Apparatus:
Coils (Induction and High Frequency), Fluoroscopes, Motor-Generators, etc.
MINIATURE INCANDESCENT LAMPS,
Candelabra, Series, Decorative, Battery
EDISON DECORATIVE & MINIATURE LAMP DEPT.
(General Electric Co.) Harrison, N. J.

A Boon to Cyclists
BURNIP'S (Patent) CHAIN LINK BRUSH.
If your dealer does not keep it send 50 cts. to
L. H. LEADAM, 81 Pine St., New York.
Agent for Kreuger & Co., 10 Exchange, London, E.C.
Kindly mention Scientific American.

MODEL 96
A Powerful Shooting Revolver of Strong and Simple Mechanism.
Send for Catalogue describing this and other models.
SMITH & WESSON,
14 Stockbridge Street, Springfield, Mass.

Cribune a Bicycle
Tested and True.

The Easiest Running Wheel in the World.
Send for Catalogue.

THE BLACK MFG. CO., ERIE, PA.

THE BICYCLE: ITS INFLUENCE IN Health and Disease.—By G. M. Hammond, M.D. A valuable and interesting paper in which the subject is exhaustively treated from the following standpoints: 1. The use of the cycle by persons in health. 2. The use of the cycle by persons diseased. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1002. Price 10 cents. To be had at this office and from all new dealers.

THE HARRINGTON & KING PERFORATING CO.
THE LARGEST MANUFACTURERS OF PERFORATED SHEET METAL IN THE WORLD.
IRON, STEEL, BRASS, TIN, ZINC, ALUMINUM, BRONZE, etc. PERFORATED IN ANY THICKNESS OF METAL. ANY SHAPE & SIZE OF HOLE. FANCY DESIGNS PERFORATED. SEND WORD WHAT YOU WANT. WE'LL DO THE WORK PROMPTLY.
CHICAGO ILL. U.S.A.
225 NORTH UNION ST.

FISCHER'S CIRCLE DIVIDER AND ANGLE PROTRACTOR
This instrument divides a circle into as many parts as there are eighths or sixteenths of an inch in its radius, by means of the points, which are marked "8" and "16." It is a very useful and time-saving novelty. Instrument in cloth covered pocket case, with directions, postpaid \$1.50. KEUFFEL & ESSER CO., Manufacturers, 44 Ann Street, New York.

The Queen Acme No. 5 Microscope
NEW MODEL AS PER CUT.
The Ideal Microscope for Amateur Research. Stands unequalled for precise and accurate adjustments and optical excellence. With objectives giving from 50 to 500 diameters, in case, \$35.00.
Send for new Microscope Catalogue F. M.
QUEEN & CO., INC.
1011 Chestnut St., Philadelphia, Pa.

At 1/4 Price
Bicycles, Watches, Guns, Buggies, Harness, Sewing Machines, Organs, Pianos, Safes, Tools. Scales of all varieties and 1000 other articles. Lists free. CHICAGO SCALE CO., Chicago, Ill.

GUNDLACH OPTICAL CO.
161-765 S. CLINTON ST. ROCHESTER, N.Y.
MANUFACTURERS OF PHOTOGRAPHIC APPARATUS.
OUR NEW CYCLE OUTFIT CAN'T BE BEATEN FOR QUALITY OR PRICE.

PRINTING INKS
The SCIENTIFIC AMERICAN is printed with CHAS. R. NEW JOHNSON & CO.'S INK, Tenth and Lombard Sts., Philadelphia, and 47 Rose St. opp. Duane, New York